

UTILITY APPLICATION

UNDER 37 CFR § 1.53(B)

TITLE: CANISTER DESIGN FOR IMPLANTABLE
CARDIOVERTER-DEFIBRILLATORS

APPLICANT(S): GUST H. BARDY, M.D.; RICCARDO CAPPATO,
M.D.; WILLIAM J. RISSMANN; GARY H.
SANDERS

Correspondence Enclosed:

Utility Application Transmittal Sheet and FY 2001
Fee Transmittal Sheet (2 pgs); Specification
(105 pgs); Claims (16 pgs); Drawings (17 pgs);
Abstract (1 pg); and Return Postcard

"EXPRESS MAIL" Mailing Label Number EL573394903US Date of Deposit August 27, 2001 I
hereby certify under 37 CFR §1.10 that this correspondence is being deposited with the United
States Postal Service as "Express Mail Post Office to Addressee" with sufficient postage on the
date indicated above and is addressed to the Commissioner for Patents, Washington, D.C. 20231.

CANISTER DESIGNS FOR IMPLANTABLE CARDIOVERTER-DEFIBRILLATORS

Inventors:

Gust H. Bardy

Riccardo Cappato

William J. Rissmann

Gary H. Sanders

032580.0029.UTL

**CANISTER DESIGNS FOR IMPLANTABLE CARDIOVERTER-
DEFIBRILLATORS**

CROSS-REFERENCE TO RELATED APPLICATIONS

5 The present application is a continuation-in-part of U.S.
patent application entitled "SUBCUTANEOUS ONLY IMPLANTABLE
CARDIOVERTER-DEFIBRILLATOR AND OPTIONAL PACER," having Serial
No. 09/663,606, filed September 18, 2000, pending, and U.S.
patent application entitled "UNITARY SUBCUTANEOUS ONLY
10 IMPLANTABLE CARDIOVERTER-DEFIBRILLATOR AND OPTIONAL PACER,"
having Serial No. 09/663,607, filed September 18, 2000, pending,
of which both applications are assigned to the assignee of the
present application, and the disclosures of both applications
are hereby incorporated by reference.

15 In addition, the present application is filed concurrently
herewith U.S. patent application entitled "DUCKBILL-SHAPED
IMPLANTABLE CARDIOVERTER-DEFIBRILLATOR AND METHOD OF USE," U.S.
patent application entitled "CERAMICS AND/OR OTHER MATERIAL
INSULATED SHELL FOR ACTIVE AND NON-ACTIVE S-ICD CAN," U.S.
20 patent application entitled "SUBCUTANEOUS ELECTRODE FOR
TRANSTHORACIC CONDUCTION WITH IMPROVED INSTALLATION
CHARACTERISTICS," U.S. patent application entitled "SUBCUTANEOUS
ELECTRODE WITH IMPROVED CONTACT SHAPE FOR TRANSTHORACIC

CONDUCTION," U.S. patent application entitled "SUBCUTANEOUS
ELECTRODE FOR TRANSTHORACIC CONDUCTION WITH HIGHLY MANEUVERABLE
INSERTION TOOL," U.S. patent application entitled "SUBCUTANEOUS
ELECTRODE FOR TRANSTHORACIC CONDUCTION WITH LOW-PROFILE
5 INSTALLATION APPENDAGE AND METHOD OF DOING SAME," U.S. patent
application entitled "SUBCUTANEOUS ELECTRODE FOR TRANSTHORACIC
CONDUCTION WITH INSERTION TOOL," U.S. patent application
entitled "METHOD OF INSERTION AND IMPLANTATION FOR IMPLANTABLE
CARDIOVERTER-DEFIBRILLATOR CANISTERS," U.S. patent application
10 entitled "RADIANT CURVED IMPLANTABLE CARDIOVERTER-DEFIBRILLATOR
CANISTER," U.S. patent application entitled "CARDIOVERTER-
DEFIBRILLATOR HAVING A FOCUSED SHOCKING AREA AND ORIENTATION
THEREOF," U.S. patent application entitled "BIPHASIC WAVEFORM
FOR ANTI-BRADYCARDIA PACING FOR A SUBCUTANEOUS IMPLANTABLE
15 CARDIOVERTER-DEFIBRILLATOR," U.S. patent application entitled
"BIPHASIC WAVEFORM FOR ANTI-TACHYCARDIA PACING FOR A
SUBCUTANEOUS IMPLANTABLE CARDIOVERTER-DEFIBRILLATOR," and U.S.
patent application entitled "POWER SUPPLY FOR A SUBCUTANEOUS
IMPLANTABLE CARDIOVERTER-DEFIBRILLATOR," the disclosures of
20 which applications are hereby incorporated by reference.

BACKGROUND OF THE INVENTION

Defibrillation/cardioversion is a technique employed to counter arrhythmic heart conditions including some tachycardias in the atria and/or ventricles. Typically, electrodes are employed to stimulate the heart with electrical impulses or shocks, of a magnitude substantially greater than pulses used in cardiac pacing.

Defibrillation/cardioversion systems include body implantable electrodes and are referred to as implantable cardioverter/defibrillators (ICDs). Such electrodes can be in the form of patches applied directly to epicardial tissue, or at the distal end regions of intravascular catheters, inserted into a selected cardiac chamber. U.S. Pat. Nos. 4,603,705, 4,693,253, 4,944,300, 5,105,810, the disclosures of which are all incorporated herein by reference, disclose intravascular or transvenous electrodes, employed either alone or in combination with an epicardial patch electrode. Compliant epicardial defibrillator electrodes are disclosed in U.S. Pat. Nos. 4,567,900 and 5,618,287, the disclosures of which are incorporated herein by reference. A sensing epicardial electrode configuration is disclosed in U.S. Pat No. 5,476,503, the disclosure of which is incorporated herein by reference.

5

20

ICDs are now an established therapy for the management of life threatening cardiac rhythm disorders, primarily ventricular fibrillation (V-Fib). ICDs are very effective at treating V-Fib, but are therapies that still require significant surgery.

5 As ICD therapy becomes more prophylactic in nature and used in progressively less ill individuals, especially children at risk of cardiac arrest, the requirement of ICD therapy to use intravenous catheters and transvenous leads is an impediment to very long term management as most individuals will begin to develop complications related to lead system malfunction sometime in the 5-10 year time frame, often earlier. In addition, chronic transvenous lead systems, their reimplantation and removals, can damage major cardiovascular venous systems and the tricuspid valve, as well as result in life threatening perforations of the great vessels and heart. Consequently, use of transvenous lead systems, despite their many advantages, are not without their chronic patient management limitations in those with life expectancies of >5 years. The problem of lead complications is even greater in children where body growth can substantially alter transvenous lead function and lead to additional cardiovascular problems and revisions. Moreover, transvenous ICD systems also increase cost and require

specialized interventional rooms and equipment as well as special skill for insertion. These systems are typically implanted by cardiac electrophysiologists who have had a great deal of extra training.

5 In addition to the background related to ICD therapy, the present invention requires a brief understanding of automatic external defibrillator (AED) therapy. AEDs employ the use of cutaneous patch electrodes to effect defibrillation under the direction of a bystander user who treats the patient suffering from V-Fib. AEDs can be as effective as an ICD if applied to the victim promptly within 2 to 3 minutes.

10 AED therapy has great appeal as a tool for diminishing the risk of death in public venues such as in air flight. However, an AED must be used by another individual, not the person suffering from the potential fatal rhythm. It is more of a public health tool than a patient-specific tool like an ICD. Because >75% of cardiac arrests occur in the home, and over half occur in the bedroom, patients at risk of cardiac arrest are often alone or asleep and can not be helped in time with an AED. 15
20 Moreover, its success depends to a reasonable degree on an acceptable level of skill and calm by the bystander user.

What is needed therefore, especially for children and for prophylactic long term use, is a combination of the two forms of therapy which would provide prompt and near-certain defibrillation, like an ICD, but without the long-term adverse sequelae of a transvenous lead system while simultaneously using most of the simpler and lower cost technology of an AED. What is also needed is a cardioverter/defibrillator that is of simple design and can be comfortably implanted in a patient for many years.

SUMMARY OF THE INVENTION

One embodiment of the present invention provides an implantable cardioverter defibrillator for subcutaneous positioning between the third rib and the twelfth rib within a patient, the implantable cardioverter-defibrillator including a housing; having a first surface and a second surface, wherein the first surface comprises an electrically insulated material and the second surface comprises an electrically conductive material; and an electrical circuit located within the housing, wherein the electrical circuit is electrically coupled to the second surface of the housing.

BRIEF DESCRIPTION OF THE DRAWINGS

For a better understanding of the invention, reference is now made to the drawings where like numerals represent similar objects throughout the figures where:

5 FIG. 1 is a schematic view of a Subcutaneous ICD (S-ICD) of the present invention;

FIG. 2 is a schematic view of an alternate embodiment of a subcutaneous electrode of the present invention;

10 FIG. 3 is a schematic view of an alternate embodiment of a subcutaneous electrode of the present invention;

FIG. 4 is a schematic view of the S-ICD and lead of FIG. 1 subcutaneously implanted in the thorax of a patient;

15 FIG. 5 is a schematic view of the S-ICD and lead of FIG. 2 subcutaneously implanted in an alternate location within the thorax of a patient;

FIG. 6 is a schematic view of the S-ICD and lead of FIG. 3 subcutaneously implanted in the thorax of a patient;

20 FIG. 7 is a schematic view of the method of making a subcutaneous path from the preferred incision and housing implantation point to a termination point for locating a subcutaneous electrode of the present invention;

FIG. 8 is a schematic view of an introducer set for performing the method of lead insertion of any of the described embodiments;

FIG. 9 is a schematic view of an alternative S-ICD of the present invention illustrating a lead subcutaneously and serpigginously implanted in the thorax of a patient for use particularly in children;

FIG. 10 is a schematic view of an alternate embodiment of an S-ICD of the present invention;

FIG. 11 is a schematic view of the S-ICD of FIG. 10 subcutaneously implanted in the thorax of a patient;

FIG. 12 is a schematic view of yet a further embodiment where the canister of the S-ICD of the present invention is shaped to be particularly useful in placing subcutaneously adjacent and parallel to a rib of a patient; and

FIG. 13 is a schematic of a different embodiment where the canister of the S-ICD of the present invention is shaped to be particularly useful in placing subcutaneously adjacent and parallel to a rib of a patient.

FIG. 14 is a schematic view of a Unitary Subcutaneous ICD (US-ICD) of the present invention;

FIG. 15 is a schematic view of the US-ICD subcutaneously implanted in the thorax of a patient;

FIG. 16 is a schematic view of the method of making a subcutaneous path from the preferred incision for implanting the
5 US-ICD.

FIG. 17 is a schematic view of an introducer for performing the method of US-ICD implantation; and

FIG. 18 is an exploded schematic view of an alternate embodiment of the present invention with a plug-in portion that contains operational circuitry and means for generating cardioversion/defibrillation shock waves.

Figure 19 is a top perspective view of an alternative S-ICD canister of the present invention depicting the top side of the canister housing and a lead electrode coupled to the S-ICD
15 canister;

Figure 20 is an exploded bottom perspective view of the S-ICD canister of Figure 19 showing an electrode in the shape of a thumbnail positioned on the bottom surface of the canister housing;

Figure 21 is a front elevational view of the S-ICD canister of Figure 19 depicting the curved canister housing;

Figure 22 is a partial schematic view of the S-ICD canister of the present invention implanted subcutaneously in the thorax of the recipient patient;

Figure 23A is a top plan view of an alternative S-ICD canister of the present invention having a duckbill-shaped end to the canister housing at the proximal end;

Figure 23B is a top plan view of an alternative S-ICD canister of the present invention having a duckbill-shaped canister housing with an alternative proximal head configuration;

Figure 24A is a top plan view of an alternative S-ICD canister of the present invention having a rectangular-shaped canister housing;

Figure 24B is a top plan view of an alternative S-ICD canister of the present invention having a square-shaped canister housing with a triangular shaped electrode;

Figure 24C is a top plan view of an alternative S-ICD canister of the present invention having a square-shaped canister housing with a square shaped electrode;

Figure 25A is a top plan view of an alternative S-ICD canister of the present invention having a tongue depressor-shaped canister housing;

Figure 25B is a top plan view of an alternative S-ICD canister of the present invention having a modified tongue depressor-shaped canister housing;

Figure 26A is a top plan view of an alternative S-ICD canister of the present invention having a multi-segment canister housing;

Figure 26B is a front elevational view of the S-ICD canister of Figure 26A depicting the curved proximal segment and the planar distal segment of the multi-segment canister housing; and

Figure 26C is a front elevational view of the S-ICD canister of Figure 26A depicting the curved proximal segment and the curved distal segment of the multi-segment canister housing.

DETAILED DESCRIPTION OF THE INVENTION

Turning now to FIG. 1, the S-ICD of the present invention is illustrated. The S-ICD consists of an electrically active canister 11 and a subcutaneous electrode 13 attached to the canister. The canister has an electrically active surface 15 that is electrically insulated from the electrode connector block 17 and the canister housing 16 via insulating area 14. The canister can be similar to numerous electrically active

canisters commercially available in that the canister will contain a battery supply, capacitor and operational circuitry. Alternatively, the canister can be thin and elongated to conform to the intercostal space. The circuitry will be able to monitor cardiac rhythms for tachycardia and fibrillation, and if detected, will initiate charging the capacitor and then delivering cardioversion /defibrillation energy through the active surface of the housing and to the subcutaneous electrode. Examples of such circuitry are described in U.S. Patent Nos. 4,693,253 and 5,105,810, the entire disclosures of which are herein incorporated by reference. The canister circuitry can provide cardioversion/ defibrillation energy in different types of waveforms. In the preferred embodiment, a 100 uF biphasic waveform is used of approximately 10-20 ms total duration and with the initial phase containing approximately 2/3 of the energy, however, any type of waveform can be utilized such as monophasic, biphasic, multiphasic or alternative waveforms as is known in the art.

In addition to providing cardioversion/ defibrillation energy, the circuitry can also provide transthoracic cardiac pacing energy. The optional circuitry will be able to monitor the heart for bradycardia and/or tachycardia rhythms. Once a

bradycardia or tachycardia rhythm is detected, the circuitry can then deliver appropriate pacing energy at appropriate intervals through the active surface and the subcutaneous electrode. Pacing stimuli will be biphasic in the preferred embodiment and
5 similar in pulse amplitude to that used for conventional transthoracic pacing.

10
15
20
25
30
35
40
45
50
55
60
65
70
75
80
85
90
95
100
105
110
115
120
125
130
135
140
145
150
155
160
165
170
175
180
185
190
195
200
205
210
215
220
225
230
235
240
245
250
255
260
265
270
275
280
285
290
295
300
305
310
315
320
325
330
335
340
345
350
355
360
365
370
375
380
385
390
395
400
405
410
415
420
425
430
435
440
445
450
455
460
465
470
475
480
485
490
495
500
505
510
515
520
525
530
535
540
545
550
555
560
565
570
575
580
585
590
595
600
605
610
615
620
625
630
635
640
645
650
655
660
665
670
675
680
685
690
695
700
705
710
715
720
725
730
735
740
745
750
755
760
765
770
775
780
785
790
795
800
805
810
815
820
825
830
835
840
845
850
855
860
865
870
875
880
885
890
895
900
905
910
915
920
925
930
935
940
945
950
955
960
965
970
975
980
985
990
995
1000
1005
1010
1015
1020
1025
1030
1035
1040
1045
1050
1055
1060
1065
1070
1075
1080
1085
1090
1095
1100
1105
1110
1115
1120
1125
1130
1135
1140
1145
1150
1155
1160
1165
1170
1175
1180
1185
1190
1195
1200
1205
1210
1215
1220
1225
1230
1235
1240
1245
1250
1255
1260
1265
1270
1275
1280
1285
1290
1295
1300
1305
1310
1315
1320
1325
1330
1335
1340
1345
1350
1355
1360
1365
1370
1375
1380
1385
1390
1395
1400
1405
1410
1415
1420
1425
1430
1435
1440
1445
1450
1455
1460
1465
1470
1475
1480
1485
1490
1495
1500
1505
1510
1515
1520
1525
1530
1535
1540
1545
1550
1555
1560
1565
1570
1575
1580
1585
1590
1595
1600
1605
1610
1615
1620
1625
1630
1635
1640
1645
1650
1655
1660
1665
1670
1675
1680
1685
1690
1695
1700
1705
1710
1715
1720
1725
1730
1735
1740
1745
1750
1755
1760
1765
1770
1775
1780
1785
1790
1795
1800
1805
1810
1815
1820
1825
1830
1835
1840
1845
1850
1855
1860
1865
1870
1875
1880
1885
1890
1895
1900
1905
1910
1915
1920
1925
1930
1935
1940
1945
1950
1955
1960
1965
1970
1975
1980
1985
1990
1995
2000
2005
2010
2015
2020
2025
2030
2035
2040
2045
2050
2055
2060
2065
2070
2075
2080
2085
2090
2095
2100
2105
2110
2115
2120
2125
2130
2135
2140
2145
2150
2155
2160
2165
2170
2175
2180
2185
2190
2195
2200
2205
2210
2215
2220
2225
2230
2235
2240
2245
2250
2255
2260
2265
2270
2275
2280
2285
2290
2295
2300
2305
2310
2315
2320
2325
2330
2335
2340
2345
2350
2355
2360
2365
2370
2375
2380
2385
2390
2395
2400
2405
2410
2415
2420
2425
2430
2435
2440
2445
2450
2455
2460
2465
2470
2475
2480
2485
2490
2495
2500
2505
2510
2515
2520
2525
2530
2535
2540
2545
2550
2555
2560
2565
2570
2575
2580
2585
2590
2595
2600
2605
2610
2615
2620
2625
2630
2635
2640
2645
2650
2655
2660
2665
2670
2675
2680
2685
2690
2695
2700
2705
2710
2715
2720
2725
2730
2735
2740
2745
2750
2755
2760
2765
2770
2775
2780
2785
2790
2795
2800
2805
2810
2815
2820
2825
2830
2835
2840
2845
2850
2855
2860
2865
2870
2875
2880
2885
2890
2895
2900
2905
2910
2915
2920
2925
2930
2935
2940
2945
2950
2955
2960
2965
2970
2975
2980
2985
2990
2995
3000
3005
3010
3015
3020
3025
3030
3035
3040
3045
3050
3055
3060
3065
3070
3075
3080
3085
3090
3095
3100
3105
3110
3115
3120
3125
3130
3135
3140
3145
3150
3155
3160
3165
3170
3175
3180
3185
3190
3195
3200
3205
3210
3215
3220
3225
3230
3235
3240
3245
3250
3255
3260
3265
3270
3275
3280
3285
3290
3295
3300
3305
3310
3315
3320
3325
3330
3335
3340
3345
3350
3355
3360
3365
3370
3375
3380
3385
3390
3395
3400
3405
3410
3415
3420
3425
3430
3435
3440
3445
3450
3455
3460
3465
3470
3475
3480
3485
3490
3495
3500
3505
3510
3515
3520
3525
3530
3535
3540
3545
3550
3555
3560
3565
3570
3575
3580
3585
3590
3595
3600
3605
3610
3615
3620
3625
3630
3635
3640
3645
3650
3655
3660
3665
3670
3675
3680
3685
3690
3695
3700
3705
3710
3715
3720
3725
3730
3735
3740
3745
3750
3755
3760
3765
3770
3775
3780
3785
3790
3795
3800
3805
3810
3815
3820
3825
3830
3835
3840
3845
3850
3855
3860
3865
3870
3875
3880
3885
3890
3895
3900
3905
3910
3915
3920
3925
3930
3935
3940
3945
3950
3955
3960
3965
3970
3975
3980
3985
3990
3995
4000
4005
4010
4015
4020
4025
4030
4035
4040
4045
4050
4055
4060
4065
4070
4075
4080
4085
4090
4095
4100
4105
4110
4115
4120
4125
4130
4135
4140
4145
4150
4155
4160
4165
4170
4175
4180
4185
4190
4195
4200
4205
4210
4215
4220
4225
4230
4235
4240
4245
4250
4255
4260
4265
4270
4275
4280
4285
4290
4295
4300
4305
4310
4315
4320
4325
4330
4335
4340
4345
4350
4355
4360
4365
4370
4375
4380
4385
4390
4395
4400
4405
4410
4415
4420
4425
4430
4435
4440
4445
4450
4455
4460
4465
4470
4475
4480
4485
4490
4495
4500
4505
4510
4515
4520
4525
4530
4535
4540
4545
4550
4555
4560
4565
4570
4575
4580
4585
4590
4595
4600
4605
4610
4615
4620
4625
4630
4635
4640
4645
4650
4655
4660
4665
4670
4675
4680
4685
4690
4695
4700
4705
4710
4715
4720
4725
4730
4735
4740
4745
4750
4755
4760
4765
4770
4775
4780
4785
4790
4795
4800
4805
4810
4815
4820
4825
4830
4835
4840
4845
4850
4855
4860
4865
4870
4875
4880
4885
4890
4895
4900
4905
4910
4915
4920
4925
4930
4935
4940
4945
4950
4955
4960
4965
4970
4975
4980
4985
4990
4995
5000
5005
5010
5015
5020
5025
5030
5035
5040
5045
5050
5055
5060
5065
5070
5075
5080
5085
5090
5095
5100
5105
5110
5115
5120
5125
5130
5135
5140
5145
5150
5155
5160
5165
5170
5175
5180
5185
5190
5195
5200
5205
5210
5215
5220
5225
5230
5235
5240
5245
5250
5255
5260
5265
5270
5275
5280
5285
5290
5295
5300
5305
5310
5315
5320
5325
5330
5335
5340
5345
5350
5355
5360
5365
5370
5375
5380
5385
5390
5395
5400
5405
5410
5415
5420
5425
5430
5435
5440
5445
5450
5455
5460
5465
5470
5475
5480
5485
5490
5495
5500
5505
5510
5515
5520
5525
5530
5535
5540
5545
5550
5555
5560
5565
5570
5575
5580
5585
5590
5595
5600
5605
5610
5615
5620
5625
5630
5635
5640
5645
5650
5655
5660
5665
5670
5675
5680
5685
5690
5695
5700
5705
5710
5715
5720
5725
5730
5735
5740
5745
5750
5755
5760
5765
5770
5775
5780
5785
5790
5795
5800
5805
5810
5815
5820
5825
5830
5835
5840
5845
5850
5855
5860
5865
5870
5875
5880
5885
5890
5895
5900
5905
5910
5915
5920
5925
5930
5935
5940
5945
5950
5955
5960
5965
5970
5975
5980
5985
5990
5995
6000
6005
6010
6015
6020
6025
6030
6035
6040
6045
6050
6055
6060
6065
6070
6075
6080
6085
6090
6095
6100
6105
6110
6115
6120
6125
6130
6135
6140
6145
6150
6155
6160
6165
6170
6175
6180
6185
6190
6195
6200
6205
6210
6215
6220
6225
6230
6235
6240
6245
6250
6255
6260
6265
6270
6275
6280
6285
6290
6295
6300
6305
6310
6315
6320
6325
6330
6335
6340
6345
6350
6355
6360
6365
6370
6375
6380
6385
6390
6395
6400
6405
6410
6415
6420
6425
6430
6435
6440
6445
6450
6455
6460
6465
6470
6475
6480
6485
6490
6495
6500
6505
6510
6515
6520
6525
6530
6535
6540
6545
6550
6555
6560
6565
6570
6575
6580
6585
6590
6595
6600
6605
6610
6615
6620
6625
6630
6635
6640
6645
6650
6655
6660
6665
6670
6675
6680
6685
6690
6695
6700
6705
6710
6715
6720
6725
6730
6735
6740
6745
6750
6755
6760
6765
6770
6775
6780
6785
6790
6795
6800
6805
6810
6815
6820
6825
6830
6835
6840
6845
6850
6855
6860
6865
6870
6875
6880
6885
6890
6895
6900
6905
6910
6915
6920
6925
6930
6935
6940
6945
6950
6955
6960
6965
6970
6975
6980
6985
6990
6995
7000
7005
7010
7015
7020
7025
7030
7035
7040
7045
7050
7055
7060
7065
7070
7075
7080
7085
7090
7095
7100
7105
7110
7115
7120
7125
7130
7135
7140
7145
7150
7155
7160
7165
7170
7175
7180
7185
7190
7195
7200
7205
7210
7215
7220
7225
7230
7235
7240
7245
7250
7255
7260
7265
7270
7275
7280
7285
7290
7295
7300
7305
7310
7315
7320
7325
7330
7335
7340
7345
7350
7355
7360
7365
7370
7375
7380
7385
7390
7395
7400
7405
7410
7415
7420
7425
7430
7435
7440
7445
7450
7455
7460
7465
7470
7475
7480
7485
7490
7495
7500
7505
7510
7515
7520
7525
7530
7535
7540
7545
7550
7555
7560
7565
7570
7575
7580
7585
7590
7595
7600
7605
7610
7615
7620
7625
7630
7635
7640
7645
7650
7655
7660
7665
7670
7675
7680
7685
7690
7695
7700
7705
7710
7715
7720
7725
7730
7735
7740
7745
7750
7755
7760
7765
7770
7775
7780
7785
7790
7795
7800
7805
7810
7815
7820
7825
7830
7835
7840
7845
7850
7855
7860
7865
7870
7875
7880
7885
7890
7895
7900
7905
7910
7915
7920
7925
7930
7935
7940
7945
7950
7955
7960
7965
7970
7975
7980
7985
7990
7995
8000
8005
8010
8015
8020
8025
8030
8035
8040
8045
8050
8055
8060
8065
8070
8075
8080
8085
8090
8095
8100
8105
8110
8115
8120
8125
8130
8135
8140
8145
8150
8155
8160
8165
8170
8175
8180
8185
8190
8195
8200
8205
8210
8215
8220
8225
8230
8235
8240
8245
8250
8255
8260
8265
8270
8275
8280
8285
8290
8295
8300
8305
8310
8315
8320
8325
8330
8335
8340
8345
8350
8355
8360
8365
8370
8375
8380
8385
8390
8395
8400
8405
8410
8415
8420
8425
8430
8435
8440
8445
8450
8455
8460
8465
8470
8475
8480
8485
8490
8495
8500
8505
8510
8515
8520
8525
8530
8535
8540
8545
8550
8555
8560
8565
8570
8575
8580
8585
8590
8595
8600
8605
8610
8615
8620
8625
8630
8635
8640
8645
8650
8655
8660
8665
8670
8675
8680
8685
8690
8695
8700
8705
8710
8715
8720
8725
8730
8735
8740
8745
8750
8755
8760
8765
8770
8775
8780
8785
8790
8795
8800
8805
8810
8815
8820
8825
8830
8835
8840
8845
8850
8855
8860
8865
8870
8875
8880
8885
8890
8895
8900
8905
8910
8915
8920
8925
8930
8935
8940
8945
8950
8955
8960
8965
8970
8975
8980
8985
8990
8995
9000
9005
9010
9015
9020
9025
9030
9035
9040
9045
9050
9055
9060
9065
9070
9075
9080
9085
9090
9095
9100
9105
9110
9115
9120
9125
9130
9135
9140
9145
9150
9155
9160
9165
9170
9175
9180
9185
9190
9195
9200
9205
9210
9215
9220
9225
9230
9235
9240
9245
9250
9255
9260
9265
9270
9275
9280
9285
9290
9295
9300
9305
9310
9315
9320
9325
9330
9335
9340
9345
9350
9355
9360
9365
9370
9375
9380
9385
9390
9395
9400
9405
9410
9415
9420
9425
9430
9435
9440
9445
9450
9455
9460
9465
9470
9475
9480
9485
9490
9495
9500
9505
9510
9515
9520
9525
9530
9535
9540
9545
9550
9555
9560
9565
9570
9575
9580
9585
9590
9595
9600
9605
9610
9615
9620
9625
9630
9635
9640
9645
9650
9655
9660
9665
9670
9675
9680
9685
9690
9695
9700
9705
9710
9715
9720
9725
9730
9735
9740
9745
9750
9755
9760
9765
9770
9775
9780
9785
9790
9795
9800
9805
9810
9815
9820
9825
9830
9835
9840
9845
9850
9855
9860
9865
9870
9875
9880
9885
9890
9895
9900
9905
9910
9915
9920
9925
9930
9935
9940
9945
9950
9955
9960
9965
9970
9975
9980
9985
9990
9995
10000
10005
10010
10015
10020
10025
10030
10035
10040
10045
10050
10055
10060
10065
10070
10075
10080
10085
10090
10095
10100
10105
10110
10115
10120
10125
10130
10135
10140
10145
10150
10155
10160
10165
10170
10175
10180
10185
10190
10195
10200
10205
10210
10215
10220
10225
10230
10235
10240
10245
10250
10255
10260
10265
10270
10275
10280
10285
10290
10295
10300
10305
103

R Cycle length instability detection algorithms. Once atrial fibrillation has been detected, the operational circuitry will then provide QRS synchronized atrial defibrillation/cardioversion using the same shock energy and waveshape characteristics used for ventricular defibrillation/ cardioversion.

The sensing circuitry will utilize the electronic signals generated from the heart and will primarily detect QRS waves. In one embodiment, the circuitry will be programmed to detect only ventricular tachycardias or fibrillations. The detection circuitry will utilize in its most direct form, a rate detection algorithm that triggers charging of the capacitor once the ventricular rate exceeds some predetermined level for a fixed period of time: for example, if the ventricular rate exceeds 240 bpm on average for more than 4 seconds. Once the capacitor is charged, a confirmatory rhythm check would ensure that the rate persists for at least another 1 second before discharge. Similarly, termination algorithms could be instituted that ensure that a rhythm less than 240 bpm persisting for at least 4 seconds before the capacitor charge is drained to an internal resistor. Detection, confirmation and termination algorithms as are described above and in the art can be modulated to increase

5 sensitivity and specificity by examining QRS beat-to-beat uniformity, QRS signal frequency content, R-R interval stability data, and signal amplitude characteristics all or part of which can be used to increase or decrease both sensitivity and specificity of S-ICD arrhythmia detection function.

10 In addition to use of the sense circuitry for detection of V-Fib or V-Tach by examining the QRS waves, the sense circuitry can check for the presence or the absence of respiration. The respiration rate can be detected by monitoring the impedance across the thorax using subthreshold currents delivered across the active can and the high voltage subcutaneous lead electrode and monitoring the frequency in undulation in the waveform that results from the undulations of transthoracic impedance during the respiratory cycle. If there is no undulation, then the patent is not respiring and this lack of respiration can be used to confirm the QRS findings of cardiac arrest. The same technique can be used to provide information about the respiratory rate or estimate cardiac output as described in U.S. Patent Nos. 6,095,987, 5,423,326, 4,450,527, the entire
20 disclosures of which are incorporated herein by reference.

The canister of the present invention can be made out of titanium alloy or other presently preferred electrically active

canister designs. However, it is contemplated that a malleable canister that can conform to the curvature of the patient's chest will be preferred. In this way the patient can have a comfortable canister that conforms to the shape of the patient's rib cage. Examples of conforming canisters are provided in U.S. Patent No. 5,645,586, the entire disclosure of which is herein incorporated by reference. Therefore, the canister can be made out of numerous materials such as medical grade plastics, metals, and alloys. In the preferred embodiment, the canister is smaller than 60 cc volume having a weight of less than 100 gms for long term wearability, especially in children. The canister and the lead of the S-ICD can also use fractal or wrinkled surfaces to increase surface area to improve defibrillation capability. Because of the primary prevention role of the therapy and the likely need to reach energies over 40 Joules, a feature of the preferred embodiment is that the charge time for the therapy, intentionally e relatively long to allow capacitor charging within the limitations of device size. Examples of small ICD housings are disclosed in U.S. Patents Nos. 5,597,956 and 5,405,363, the entire disclosures of which are herein incorporated by reference.

Different subcutaneous electrodes 13 of the present invention are illustrated in FIGS. 1-3. Turning to FIG. 1, the lead 21 for the subcutaneous electrode is preferably composed of silicone or polyurethane insulation. The electrode is connected to the canister at its proximal end via connection port 19 which is located on an electrically insulated area 17 of the canister. The electrode illustrated is a composite electrode with three different electrodes attached to the lead. In the embodiment illustrated, an optional anchor segment 52 is attached at the most distal end of the subcutaneous electrode for anchoring the electrode into soft tissue such that the electrode does not dislodge after implantation.

The most distal electrode on the composite subcutaneous electrode is a coil electrode 27 that is used for delivering the high voltage cardioversion/ defibrillation energy across the heart. The coil cardioversion/defibrillation electrode is about 5-10 cm in length. Proximal to the coil electrode are two sense electrodes, a first sense electrode 25 is located proximally to the coil electrode and a second sense electrode 23 is located proximally to the first sense electrode. The sense electrodes are spaced far enough apart to be able to have good QRS detection. This spacing can range from 1 to 10 cm with 4 cm

being presently preferred. The electrodes may or may not be circumferential with the preferred embodiment. Having the electrodes non-circumferential and positioned outward, toward the skin surface, is a means to minimize muscle artifact and enhance QRS signal quality. The sensing electrodes are electrically isolated from the cardioversion/defibrillation electrode via insulating areas 29. Similar types of cardioversion/defibrillation electrodes are currently commercially available in a transvenous configuration. For example, U.S. Patent No. 5,534,022, the entire disclosure of which is herein incorporated by reference, discloses a composite electrode with a coil cardioversion/defibrillation electrode and sense electrodes. Modifications to this arrangement is contemplated within the scope of the invention. One such modification is illustrated in FIG. 2 where the two sensing electrodes 25 and 23 are non-circumferential sensing electrodes and one is located at the distal end, the other is located proximal thereto with the coil electrode located in between the two sensing electrodes. In this embodiment the sense electrodes are spaced about 6 to about 12 cm apart depending on the length of the coil electrode used. FIG. 3 illustrates yet a further embodiment where the two sensing

electrodes are located at the distal end to the composite electrode with the coil electrode located proximally thereto. Other possibilities exist and are contemplated within the present invention. For example, having only one sensing
5 electrode, either proximal or distal to the coil cardioversion/defibrillation electrode with the coil serving as both a sensing electrode and a cardioversion/defibrillation electrode.

It is also contemplated within the scope of the invention that the sensing of QRS waves (and transthoracic impedance) can be carried out via sense electrodes on the canister housing or
10 in combination with the cardioversion/defibrillation coil electrode and/or the subcutaneous lead sensing electrode(s). In this way, sensing could be performed via the one coil electrode located on the subcutaneous electrode and the active surface on the canister housing. Another possibility would be to have only
15 one sense electrode located on the subcutaneous electrode and the sensing would be performed by that one electrode and either the coil electrode on the subcutaneous electrode or by the active surface of the canister. The use of sensing electrodes
20 on the canister would eliminate the need for sensing electrodes on the subcutaneous electrode. It is also contemplated that the subcutaneous electrode would be provided with at least one sense

electrode, the canister with at least one sense electrode, and
if multiple sense electrodes are used on either the subcutaneous
electrode and/or the canister, that the best QRS wave detection
combination will be identified when the S-ICD is implanted and
5 this combination can be selected, activating the best sensing
arrangement from all the existing sensing possibilities.
Turning again to FIG. 2, two sensing electrodes 26 and 28 are
located on the electrically active surface 15 with electrical
insulator rings 30 placed between the sense electrodes and the
10 active surface. These canister sense electrodes could be
switched off and electrically insulated during and shortly after
defibrillation/ cardioversion shock delivery. The canister
sense electrodes may also be placed on the electrically inactive
surface of the canister. In the embodiment of FIG. 2, there are
15 actually four sensing electrodes, two on the subcutaneous lead
and two on the canister. In the preferred embodiment, the
ability to change which electrodes are used for sensing would be
a programmable feature of the S-ICD to adapt to changes in the
patient physiology and size (in the case of children) over time.
20 The programming could be done via the use of physical switches
on the canister, or as presently preferred, via the use of a

programming wand or via a wireless connection to program the circuitry within the canister.

The canister could be employed as either a cathode or an anode of the S-ICD cardioversion/defibrillation system. If the canister is the cathode, then the subcutaneous coil electrode would be the anode. Likewise, if the canister is the anode, then the subcutaneous electrode would be the cathode.

The active canister housing will provide energy and voltage intermediate to that available with ICDs and most AEDs. The typical maximum voltage necessary for ICDs using most biphasic waveforms is approximately 750 Volts with an associated maximum energy of approximately 40 Joules. The typical maximum voltage necessary for AEDs is approximately 2000-5000 Volts with an associated maximum energy of approximately 200-360 Joules depending upon the model and waveform used. The S-ICD of the present invention uses maximum voltages in the range of about 700 to about 3150 Volts and is associated with energies of about 40 to about 210 Joules. The capacitance of the S-ICD could range from about 50 to about 200 micro farads.

The sense circuitry contained within the canister is highly sensitive and specific for the presence or absence of life threatening ventricular arrhythmias. Features of the detection

algorithm are programmable and the algorithm is focused on the detection of V-FIB and high rate V-TACH (>240 bpm). Although the S-ICD of the present invention may rarely be used for an actual life threatening event, the simplicity of design and implementation allows it to be employed in large populations of patients at modest risk with modest cost by non-cardiac electrophysiologists. Consequently, the S-ICD of the present invention focuses mostly on the detection and therapy of the most malignant rhythm disorders. As part of the detection algorithm's applicability to children, the upper rate range is programmable upward for use in children, known to have rapid supraventricular tachycardias and more rapid ventricular fibrillation. Energy levels also are programmable downward in order to allow treatment of neonates and infants.

Turning now to FIG. 4, the optimal subcutaneous placement of the S-ICD of the present invention is illustrated. As would be evidence to a person skilled in the art, the actual location of the S-ICD is in a subcutaneous space that is developed during the implantation process. The heart is not exposed during this process and the heart is schematically illustrated in the figures only for help in understanding where the canister and coil electrode are three dimensionally located in the left mid-

clavicular line approximately at the level of the inframammary crease at approximately the 5th rib. The lead 21 of the subcutaneous electrode traverses in a subcutaneous path around the thorax terminating with its distal electrode end at the posterior axillary line ideally just lateral to the left scapula. This way the canister and subcutaneous cardioversion/defibrillation electrode provide a reasonably good pathway for current delivery to the majority of the ventricular myocardium.

FIG. 5 illustrates a different placement of the present invention. The S-ICD canister with the active housing is located in the left posterior axillary line approximately lateral to the tip of the inferior portion of the scapula. This location is especially useful in children. The lead 21 of the subcutaneous electrode traverses in a subcutaneous path around the thorax terminating with its distal electrode end at the anterior precordial region, ideally in the inframammary crease. FIG. 6 illustrates the embodiment of FIG. 1 subcutaneously implanted in the thorax with the proximal sense electrodes 23 and 25 located at approximately the left axillary line with the cardioversion/defibrillation electrode just lateral to the tip of the inferior portion of the scapula.

FIG. 7 schematically illustrates the method for implanting the S-ICD of the present invention. An incision 31 is made in the left anterior axillary line approximately at the level of the cardiac apex. This incision location is distinct from that chosen for S-ICD placement and is selected specifically to allow both canister location more medially in the left inframammary crease and lead positioning more posteriorly via the introducer set (described below) around to the left posterior axillary line lateral to the left scapula. That said, the incision can be anywhere on the thorax deemed reasonably by the implanting physician although in the preferred embodiment, the S-ICD of the present invention will be applied in this region. A subcutaneous pathway 33 is then created medially to the inframmary crease for the canister and posteriorly to the left posterior axillary line lateral to the left scapula for the lead.

The S-ICD canister 11 is then placed subcutaneously at the location of the incision or medially at the subcutaneous region at the left inframmary crease. The subcutaneous electrode 13 is placed with a specially designed curved introducer set 40 (see FIG. 8). The introducer set comprises a curved trocar 42 and a stiff curved peel away sheath 44. The peel away sheath is

curved to allow for placement around the rib cage of the patient in the subcutaneous space created by the trocar. The sheath has to be stiff enough to allow for the placement of the electrodes without the sheath collapsing or bending. Preferably the sheath is made out of a biocompatible plastic material and is perforated along its axial length to allow for it to split apart into two sections. The trocar has a proximal handle 41 and a curved shaft 43. The distal end 45 of the trocar is tapered to allow for dissection of a subcutaneous path 33 in the patient. Preferably, the trocar is cannulated having a central Lumen 46 and terminating in an opening 48 at the distal end. Local anesthetic such as lidocaine can be delivered, if necessary, through the lumen or through a curved and elongated needle designed to anesthetize the path to be used for trocar insertion should general anesthesia not be employed. The curved peel away sheath 44 has a proximal pull tab 49 for breaking the sheath into two halves along its axial shaft 47. The sheath is placed over a guidewire inserted through the trocar after the subcutaneous path has been created. The subcutaneous pathway is then developed until it terminates subcutaneously at a location that, if a straight line were drawn from the canister location to the path termination point the line would intersect a

substantial portion of the left ventricular mass of the patient. The guidewire is then removed leaving the peel away sheath. The subcutaneous lead system is then inserted through the sheath until it is in the proper location. Once the subcutaneous lead system is in the proper location, the sheath is split in half using the pull tab 49 and removed. If more than one subcutaneous electrode is being used, a new curved peel away sheath can be used for each subcutaneous electrode.

The S-ICD will have prophylactic use in adults where chronic transvenous/epicardial ICD lead systems pose excessive risk or have already resulted in difficulty, such as sepsis or lead fractures. It is also contemplated that a major use of the S-ICD system of the present invention will be for prophylactic use in children who are at risk for having fatal arrhythmias, where chronic transvenous lead systems pose significant management problems. Additionally, with the use of standard transvenous ICDs in children, problems develop during patient growth in that the lead system does not accommodate the growth. FIG. 9 illustrates the placement of the S-ICD subcutaneous lead system such that the problem that growth presents to the lead system is overcome. The distal end of the subcutaneous electrode is placed in the same location as described above

providing a good location for the coil
cardioversion/defibrillation electrode 27 and the sensing
electrodes 23 and 25. The insulated lead 21, however is no
longer placed in a taught configuration. Instead, the lead is
serpiginously placed with a specially designed introducer trocar
and sheath such that it has numerous waves or bends. As the
child grows, the waves or bends will straighten out lengthening
the lead system while maintaining proper electrode placement.
Although it is expected that fibrous scarring especially around
the defibrillation coil will help anchor it into position to
maintain its posterior position during growth, a lead system
with a distal tine or screw electrode anchoring system 52 can
also be incorporated into the distal tip of the lead to
facilitate lead stability (see FIG. 1). Other anchoring systems
can also be used such as hooks, sutures, or the like.

FIGS. 10 and 11 illustrate another embodiment of the
present S-ICD invention. In this embodiment there are two
subcutaneous electrodes 13 and 13' of opposite polarity to the
canister. The additional subcutaneous electrode 13' is
essentially identical to the previously described electrode. In
this embodiment the cardioversion/defibrillation energy is
delivered between the active surface of the canister and the two

coil electrodes 27 and 27'. Additionally, provided in the canister is means for selecting the optimum sensing arrangement between the four sense electrodes 23, 23', 25, and 25'. The two electrodes are subcutaneously placed on the same side of the heart. As illustrated in FIG. 6, one subcutaneous electrode 13 is placed inferiorly and the other electrode 13' is placed superiorly. It is also contemplated with this dual subcutaneous electrode system that the canister and one subcutaneous electrode are the same polarity and the other subcutaneous electrode is the opposite polarity.

Turning now to FIGS. 12 and 13, further embodiments are illustrated where the canister 11 of the S-ICD of the present invention is shaped to be particularly useful in placing subcutaneously adjacent and parallel to a rib of a patient. The canister is long, thin, and curved to conform to the shape of the patient's rib. In the embodiment illustrated in FIG. 12, the canister has a diameter ranging from about 0.5 cm to about 2 cm without 1 cm being presently preferred. Alternatively, instead of having a circular cross sectional area, the canister could have a rectangular or square cross sectional area as illustrated in FIG. 13 without falling outside of the scope of the present invention. The length of the canister can vary

depending on the size of the patient's thorax. Currently the canister is about 5 cm to about 15 cm long with about 10 being presently preferred. The canister is curved to conform to the curvature of the ribs of the thorax. The radius of the curvature will vary depending on the size of the patient, with smaller radiuses for smaller patients and larger radiuses for larger patients. The radius of the curvature can range from about 5 cm to about 35 cm depending on the size of the patient. Additionally, the radius of the curvature need not be uniform throughout the canister such that it can be shaped closer to the shape of the ribs. The canister has an active surface, 15 that is located on the interior (concave) portion of the curvature and an inactive surface 16 that is located on the exterior (convex) portion of the curvature. The leads of these embodiments, which are not illustrated except for the attachment port.19 and the proximal end of the lead 21, can be any of the leads previously described above, with the lead illustrated in FIG. 1 being presently preferred.

The circuitry of this canister is similar to the circuitry described above. Additionally, the canister can optionally have at least one sense electrode located on either the active surface of the inactive surface and the circuitry within the

canister can be programmable as described above to allow for the selection of the best sense electrodes. It is presently preferred that the canister have two sense electrodes 26 and 28 located on the inactive surface of the canisters as illustrated, where the electrodes are spaced from about 1 to about 10 cm apart with a spacing of about 3 cm being presently preferred. However, the sense electrodes can be located on the active surface as described above.

It is envisioned that the embodiment of FIG. 12 will be subcutaneously implanted adjacent and parallel to the left anterior 5th rib, either between the 4th and 5th ribs or between the 5th and 6th ribs. However other locations can be used.

Another component of the S-ICD of the present invention is a cutaneous test electrode system designed to simulate the subcutaneous high voltage shock electrode system as well as the QRS cardiac rhythm detection system. This test electrode system is comprised of a cutaneous patch electrode of similar surface area and impedance to that of the S-ICD canister itself together with a cutaneous strip electrode comprising a defibrillation strip as well as two button electrodes for sensing of the QRS. Several cutaneous strip electrodes are available to allow for

testing various bipole spacings to optimize signal detection comparable to the implantable system.

Figures 14 to 18 depict particular US-ICD embodiments of the present invention. The various sensing, shocking and pacing circuitry, described in detail above with respect to the S-ICD
5 embodiments, may additionally be incorporated into the following US-ICD embodiments. Furthermore, particular aspects of any individual S-ICD embodiment discussed above, may be incorporated, in whole or in part, into the US-ICD embodiments
10 depicted in the following figures.

Turning now to Fig. 14, the US-ICD of the present invention is illustrated. The US-ICD consists of a curved housing 1211 with a first and second end. The first end 1413 is thicker than the second end 1215. This thicker area houses a battery supply, capacitor and operational circuitry for the US-ICD. The
15 circuitry will be able to monitor cardiac rhythms for tachycardia and fibrillation, and if detected, will initiate charging the capacitor and then delivering cardioversion/defibrillation energy through the two
20 cardioversion/defibrillating electrodes 1417 and 1219 located on the outer surface of the two ends of the housing. The circuitry can provide cardioversion/defibrillation energy in different

types of waveforms. In the preferred embodiment, a 100 uF biphasic waveform is used of approximately 10-20 ms total duration and with the initial phase containing approximately 2/3 of the energy, however, any type of waveform can be utilized
5 such as monophasic, biphasic, multiphasic or alternative waveforms as is known in the art.

The housing of the present invention can be made out of titanium alloy or other presently preferred ICD designs. It is contemplated that the housing is also made out of biocompatible plastic materials that electronically insulate the electrodes from each other. However, it is contemplated that a malleable canister that can conform to the curvature of the patient's chest will be preferred. In this way the patient can have a comfortable canister that conforms to the unique shape of the patient's rib cage. Examples of conforming ICD housings are provided in U.S. Patent No. 5,645,586, the entire disclosure of which is herein incorporated by reference. In the preferred embodiment, the housing is curved in the shape of a 5th rib of a person. Because there are many different sizes of people, the
20 housing will come in different incremental sizes to allow a good match between the size of the rib cage and the size of the US-ICD. The length of the US-ICD will range from about 15 to about

50 cm. Because of the primary preventative role of the therapy and the need to reach energies over 40 Joules, a feature of the preferred embodiment is that the charge time for the therapy, intentionally be relatively long to allow capacitor charging within the limitations of device size.

The thick end of the housing is currently needed to allow for the placement of the battery supply, operational circuitry, and capacitors. It is contemplated that the thick end will be about 0.5 cm to about 2 cm wide with about 1 cm being presently preferred. As microtechnology advances, the thickness of the housing will become smaller.

The two cardioversion/defibrillation electrodes on the housing are used for delivering the high voltage cardioversion/defibrillation energy across the heart. In the preferred embodiment, the cardioversion/defibrillation electrodes are coil electrodes, however, other cardioversion/defibrillation electrodes could be used such as having electrically isolated active surfaces or platinum alloy electrodes. The coil cardioversion/defibrillation electrodes are about 5-10 cm in length. Located on the housing between the two cardioversion/defibrillation electrodes are two sense electrodes 1425 and 1427. The sense electrodes are spaced far

enough apart to be able to have good QRS detection. This spacing can range from 1 to 10 cm with 4 cm being presently preferred. The electrodes may or may not be circumferential with the preferred embodiment. Having the electrodes non-circumferential and positioned outward, toward the skin surface, is a means to minimize muscle artifact and enhance QRS signal quality. The sensing electrodes are electrically isolated from the cardioversion/defibrillation electrode via insulating areas 1423. Analogous types of cardioversion/defibrillation electrodes are currently commercially available in a transvenous configuration. For example, U.S. Patent No. 5,534,022, the entire disclosure of which is herein incorporated by reference, discloses a composite electrode with a coil cardioversion/defibrillation electrode and sense electrodes. Modifications to this arrangement is contemplated within the scope of the invention. One such modification is to have the sense electrodes at the two ends of the housing and have the cardioversion/defibrillation electrodes located in between the sense electrodes. Another modification is to have three or more sense electrodes spaced throughout the housing and allow for the selection of the two best sensing electrodes. If three or more sensing electrodes are used, then the ability to change which

electrodes are used for sensing would be a programmable feature of the US-ICD to adapt to changes in the patient physiology and size over time. The programming could be done via the use of physical switches on the canister, or as presently preferred, via the use of a programming wand or via a wireless connection to program the circuitry within the canister.

Turning now to Fig. 15, the optimal subcutaneous placement of the US-ICD of the present invention is illustrated. As would be evident to a person skilled in the art, the actual location of the US-ICD is in a subcutaneous space that is developed during the implantation process. The heart is not exposed during this process and the heart is schematically illustrated in the figures only for help in understanding where the device and its various electrodes are three dimensionally located in the thorax of the patient. The US-ICD is located between the left mid-clavicular line approximately at the level of the inframammary crease at approximately the 5th rib and the posterior axillary line, ideally just lateral to the left scapula. This way the US-ICD provides a reasonably good pathway for current delivery to the majority of the ventricular myocardium.

Fig. 16 schematically illustrates the method for implanting the US-ICD of the present invention. An incision 1631 is made in the left anterior axillary line approximately at the level of the cardiac apex. A subcutaneous pathway is then created that extends posteriorly to allow placement of the US-ICD. The incision can be anywhere on the thorax deemed reasonable by the implanting physician although in the preferred embodiment, the US-ICD of the present invention will be applied in this region. The subcutaneous pathway is created medially to the inframammary crease and extends posteriorly to the left posterior axillary line. The pathway is developed with a specially designed curved introducer 1742 (see Fig. 17). The trocar has a proximal handle 1641 and a curved shaft 1643. The distal end 1745 of the trocar is tapered to allow for dissection of a subcutaneous path in the patient. Preferably, the trocar is cannulated having a central lumen 1746 and terminating in an opening 1748 at the distal end. Local anesthetic such as lidocaine can be delivered, if necessary, through the lumen or through a curved and elongated needle designed to anesthetize the path to be used for trocar insertion should general anesthesia not be employed. Once the subcutaneous pathway is developed, the US-ICD is implanted in

the subcutaneous space, the skin incision is closed using standard techniques.

As described previously, the US-ICDs of the present invention vary in length and curvature. The US-ICDs are provided in incremental sizes for subcutaneous implantation in different sized patients. Turning now to Fig. 18, a different embodiment is schematically illustrated in exploded view which provides different sized US-ICDs that are easier to manufacture.

The different sized US-ICDs will all have the same sized and shaped thick end 1413. The thick end is hollow inside allowing for the insertion of a core operational member 1853. The core member comprises a housing 1857 which contains the battery supply, capacitor and operational circuitry for the US-ICD. The proximal end of the core member has a plurality of electronic plug connectors. Plug connectors 1861 and 1863 are electronically connected to the sense electrodes via pressure fit connectors (not illustrated) inside the thick end which are standard in the art. Plug connectors 1865 and 1867 are also electronically connected to the cardioverter/defibrillator electrodes via pressure fit connectors inside the thick end. The distal end of the core member comprises an end cap 1855, and a ribbed fitting 1859 which creates a water-tight seal when the

core member is inserted into opening 1851 of the thick end of the US-ICD.

The core member of the different sized and shaped US-ICD will all be the same size and shape. That way, during an implantation procedures, multiple sized US-ICDs can be available for implantation, each one without a core member. Once the implantation procedure is being performed, then the correct sized US-ICD can be selected and the core member can be inserted into the US-ICD and then programmed as described above. Another advantage of this configuration is when the battery within the core member needs replacing it can be done without removing the entire US-ICD.

Figures 19-26 refer generally to alternative S-ICD/US-ICD canister embodiments. Although the following canister designs, various material constructions, dimensions and curvatures, discussed in detail below, may be incorporated into either S-ICD or US-ICD canister embodiments, hereinafter, these attributes will be discussed solely with respect to S-ICDs.

The canisters illustrated in these Figures possess a configuration that may 1) aid in the initial canister implantation; 2) restrict canister displacement once properly positioned; 3) create a consistently focused array of energy

delivered toward the recipient's heart with less disbursement to other areas of the thorax; 4) allow for good signal reception from the heart by an S-ICD system; or 5) provide significant comfort and long-term wearability in a broad spectrum of patients with differing thoracic sizes and shapes. More particularly, Figures 19-26 detail various material constructions, dimensions and curvatures that are incorporated within the numerous S-ICD canister designs detailed in Figures 19-26C.

Referring now to the particular embodiments, Figure 19 depicts an S-ICD canister 190 of an embodiment of the present invention. The shell of the S-ICD canister 190 comprises a hermetically sealed housing 192 that encases the electronics for the S-ICD canister 190. As with the previously described S-ICD devices, the electronics of the present embodiment include, at a minimum, a battery supply, a capacitor and operational circuitry. Figure 19 further depicts a lead electrode 191 coupled to the shell of the canister through a lead 193. A dorsal fin 197 may be disposed on the lead electrode 191 to facilitate the positioning of the lead electrode.

The S-ICD devices of the present invention provide an energy (electric field strength (V/cm), current density (A/cm²),

10 15 20 25 30 35 40 45 50 55 60 65 70 75 80 85 90 95 100 105 110 115 120 125 130 135 140 145 150 155 160 165 170 175 180 185 190 195 200 205 210 215 220 225 230 235 240 245 250 255 260 265 270 275 280 285 290 295 300 305 310 315 320 325 330 335 340 345 350 355 360 365 370 375 380 385 390 395 400 405 410 415 420 425 430 435 440 445 450 455 460 465 470 475 480 485 490 495 500 505 510 515 520 525 530 535 540 545 550 555 560 565 570 575 580 585 590 595 600 605 610 615 620 625 630 635 640 645 650 655 660 665 670 675 680 685 690 695 700 705 710 715 720 725 730 735 740 745 750 755 760 765 770 775 780 785 790 795 800 805 810 815 820 825 830 835 840 845 850 855 860 865 870 875 880 885 890 895 900 905 910 915 920 925 930 935 940 945 950 955 960 965 970 975 980 985 990 995

voltage gradient (V/cm) or other measured unit of energy) to a patient's heart. S-ICD devices of the present invention will generally use voltages in the range of 700 V to 3150 V, requiring energies of approximately 40 J to 210 J. These energy requirements will vary, however, depending upon the form of treatment, the proximity of the canister from the patient's heart, the relative relationship of the S-ICD canister's electrode to the lead electrode, the nature of the patient's underlying heart disease, the specific cardiac disorder being treated, and the ability to overcome diversion of the S-ICD electrical output into other thoracic tissues.

Ideally, the emitted energy from the S- ICD device will be directed into the patient's anterior mediastinum, through the majority of the heart, and out to the coupled lead electrode positioned in the posterior, posterolateral and/or lateral thoracic locations. Furthermore, it is desirable that the S-ICD canister 190 be capable of delivering this directed energy, as a general rule, at an adequate effective field strength of about 3-5 V/cm to approximately 90 percent of a patient's ventricular myocardium using a biphasic waveform. This delivered effective field strength should be adequate for defibrillation of the

patient's heart - an intended application of an embodiment of the present invention.

Increased energy requirements necessitate larger, or alternatively, additional batteries and capacitors. The latter
5 of these two options is often more desirable in order to reduce the overall depth of the resulting S-ICD canister 190. Increasing the number of batteries and capacitors, however, will increase the length and possibly the depth of the S-ICD canister
10 190. Therefore, numerous S-ICD devices of varying depth, widths and lengths are manufactured to accommodate the particular energy needs of a variety of patient recipients. For example, an overweight adult male may require a larger and bulkier S-ICD
15 canister 190 than a young child. In particular, the young child is generally smaller, has a relatively lower resistance to current flow, and contains less current diverting body mass than the overweight adult male. As a result, the energy required to deliver an effective therapy to the young child's heart may be considerably less than for the overweight adult male, and therefore, the young child may utilize a smaller and more
20 compact S-ICD canister 190. In addition, one may find that individuals, despite equivalent body size, may have different therapy requirements because of differences in their underlying

heart disease. This may allow some patients to receive a smaller canister compared to another patient of equal body size but with a different type of heart disease.

10 15 20 25 30 35 40 45 50 55 60 65 70 75 80 85 90 95 100 105 110 115 120 125 130 135 140 145 150 155 160 165 170 175 180 185 190 195 200 205 210 215 220 225 230 235 240 245 250 255 260 265 270 275 280 285 290 295 300 305 310 315 320 325 330 335 340 345 350 355 360 365 370 375 380 385 390 395 400 405 410 415 420 425 430 435 440 445 450 455 460 465 470 475 480 485 490 495 500 505 510 515 520 525 530 535 540 545 550 555 560 565 570 575 580 585 590 595 600 605 610 615 620 625 630 635 640 645 650 655 660 665 670 675 680 685 690 695 700 705 710 715 720 725 730 735 740 745 750 755 760 765 770 775 780 785 790 795 800 805 810 815 820 825 830 835 840 845 850 855 860 865 870 875 880 885 890 895 900 905 910 915 920 925 930 935 940 945 950 955 960 965 970 975 980 985 990 995

The spatial requirements of a resulting S-ICD canister 190 are additionally dependent upon the type of operational circuitry used within the device. The S-ICD canister 190 may be programmed to monitor cardiac rhythms for tachycardia and fibrillation, and if detected, will initiate charging the capacitor(s) to deliver the appropriate cardioversion/defibrillation energy. Examples of such circuitry are described in U.S. Patent Nos. 4,693,253 and 5,105,810, and are incorporated herein by reference. The S-ICD canister 190 may additionally be provided with operational circuitry for transthoracic cardiac pacing. This optional circuitry monitors the heart for bradycardia and/or tachycardia rhythms. In the event a bradycardia or tachycardia rhythm is detected, the operational circuitry delivers the appropriate pacing energy at the appropriate intervals to treat the disorder.

20 In additional embodiments, the operational circuitry may be: 1) programmed to deliver low amplitude shocks on the T-wave for induction of ventricular fibrillation for testing the S-ICD canister's performance; 2) programmed for rapid ventricular

10 15 20 25 30 35 40 45 50 55 60 65 70 75 80 85 90 95 100 105 110 115 120 125 130 135 140 145 150 155 160 165 170 175 180 185 190 195 200 205 210 215 220 225 230 235 240 245 250 255 260 265 270 275 280 285 290 295 300 305 310 315 320 325 330 335 340 345 350 355 360 365 370 375 380 385 390 395 400 405 410 415 420 425 430 435 440 445 450 455 460 465 470 475 480 485 490 495 500 505 510 515 520 525 530 535 540 545 550 555 560 565 570 575 580 585 590 595 600 605 610 615 620 625 630 635 640 645 650 655 660 665 670 675 680 685 690 695 700 705 710 715 720 725 730 735 740 745 750 755 760 765 770 775 780 785 790 795 800 805 810 815 820 825 830 835 840 845 850 855 860 865 870 875 880 885 890 895 900 905 910 915 920 925 930 935 940 945 950 955 960 965 970 975 980 985 990 995 1000

pacing to either induce a tachyarrhythmia or to terminate one;
3) programmed to detect the presence of atrial fibrillation;
and/or 4) programmed to detect ventricular fibrillation or
ventricular tachycardia by examining QRS waves, all of which are
described in detail above. Additional operational circuitry,
being known in the art for sensing, shocking and pacing the
heart, are additionally incorporated herein as being within the
spirit and scope of the present invention.

The primary function of the canister housing 192 is to
provide a protective barrier between the electrical components
held within its confines and the surrounding environment. The
canister housing 192, therefore, must possess sufficient
hardness to protect its contents. Materials possessing this
hardness may include numerous suitable biocompatible materials
such as medical grade plastics, ceramics, metals and alloys.
Although the materials possessing such hardnesses are generally
rigid, in particular embodiments, it is desirable to utilize
materials that are pliable or compliant. More specifically, it
is desirable that the canister housing 192 be capable of
partially yielding in its overall form without fracturing.

Compliant canister housings 192 often provide increased
comfort when implanted in patient recipients. S-ICD canisters

190 formed from such materials permit limited, but significant,
deflection of the canister housing 192 with certain thoracic
motions. Examples of permitted deflections are ones that are
applied to the canister housing 192 by surrounding muscle
5 tissue. The use of a compliant canister housing is particularly
beneficial in canister housing embodiments that extend over a
significant portion of a patient's thorax. The compliant
material in these embodiment may comprise a portion of the
canister housing, or alternatively, may comprise the canister
10 housing in its entirety. The correct material selection (or
combination thereof), therefore, is helpful in eliminating
patient awareness of the device and in improving the long-term
wearability of the implanted device.

Materials selected for the canister housing 192 should
15 further be capable of being sterilized. Often commercial
sterilization processes involve exposure to elevated
temperatures, pressures or chemical treatments. It is
important, therefore, that the materials used in forming the
canister housing be capable of withstanding such exposures
20 without degrading or otherwise compromising their overall
integrity.

Polymeric materials suitable for the canister housing 192 of the present invention include polyurethanes, polyamides, polyetheretherketones (PEEK), polyether block amides (PEBA), polytetrafluoroethylene (PTFE), silicones, and mixtures thereof.

5 Ceramic materials suitable for the canister housing 192 of the present invention include zirconium ceramics and aluminum-based ceramics. Metallic materials suitable for the canister housing 192 of the present invention include stainless steel, and titanium. Alloys suitable for the canister housing 192 of the present invention include stainless steel alloys and titanium alloys such as nickel titanium. In certain embodiments of the present invention, classes of materials may be combined in forming the canister housing 192. For example, a nonconductive polymeric coating, such as parylene, may be selectively applied over a titanium alloy canister housing 192 surface in order to allow only a specific surface area, such as that at the undersurface of the duckbill distal end, to receive signals and/or apply therapy.

In general, it is desirable to maintain the size of the S-
20 ICD canister housing 192 under a total volume of approximately 50 cubic centimeters. In alternative embodiments of the present invention, it is desirable to maintain the size of the S-ICD

canister housing 192 under a total volume of approximately 100 cubic centimeters. In yet alternative embodiments of the present invention, it is desirable to maintain the size of the S-ICD canister housing 192 under a total volume of approximately 120 cubic centimeters.

Moreover, it is additionally desirable to maintain the total weight of the S-ICD canister 190, as a whole (including the canister housing, operational circuitry, capacitors and batteries), under approximately 50 grams. In alternative embodiments of the present invention, it is desirable to maintain the total weight of the S-ICD canister 190 under approximately 100 grams. In yet alternative embodiments of the present invention, it is desirable to maintain the total weight of the S-ICD canister 190 under approximately 150 grams.

Maintaining the weight and size within the above identified parameters is primarily for patient comfort depending upon the shape of the device. The implantation of a S-ICD canister 190 is a long-term solution to heart dysfunction, and as such, will ideally remain in the patient until the device's batteries need replacement or an alternative therapy eventually leads to its removal. Accordingly, a considerable amount of engineering is

devoted to minimizing discomfort associated with the installed device.

Weight and size considerations are particularly important to younger patient recipients. Children possessing ICDs are more likely to be cognitive of any additional weight or bulkiness associated with heavier and/or larger devices. The present invention overcomes these problems by designing a S-ICD canister 190 that takes into consideration the concerns of these smaller sized patient recipients. For example, lighter materials may be utilized to minimize discomfort associated with heavier materials. Furthermore, the S-ICD canister 190 (length, width and depth) in its entirety, or only a portion thereof, may be modified in order to accommodate a variety of sized patient recipients. For example, the shape of the S-ICD canister housing 192 may also be manufactured in a variety of anatomical configurations to better insure comfort and performance in younger children or smaller adults, throughout the life of their S-ICD canisters 190. In order to accommodate certain patients, a physician may place the canister 190 posteriorly with the lead electrode positioned anteriorly with the patient's body, the reverse of the canister's 190 usual positioning. This canister 190 placement is particularly useful when implanted in very

small children. Such canister 190 placement generally optimizes comfort for these smaller stature recipients. Moreover, the shape of the canister 190 may be altered specifically to conform to a female's thorax, where breast tissue may alter comfort and performance requirements.

Referring now to specific portions of the canister housing 192, Figure 19 depicts a canister housing 192 in accordance with one embodiment of the present invention having a top surface 194, a bottom surface 196 and surrounding sides 198 connecting these two surfaces. The S-ICD canister housing 192 depicted in Figure 19 further includes a distal end 200 and a proximal end 202. In particular canister housing embodiments, the canister housing 192 may lack a proximal end and a distal end.

The top surface 194 of the canister housing 192 is generally smooth and void of appendages and apertures. The smooth top surface 194 enables the S-ICD canister 190 to advance effortlessly through the subcutaneous tissues during an implantation procedure. Smoothing the top surface 194 reduces the coefficient of friction of the S-ICD canister 190. Such measures reduce abrasion, and concurrently, also reduce inflammation associated with the device's insertion and advancement. The benefits of a reduction in surface friction

also continues on long after implantation through a significant reduction in inflammation and soreness, lending to an overall heightened feeling of wearability and comfort.

In alternative embodiments, the top surface 194 of the canister housing 192 may include one or more apertures, sensors, electrodes, appendages, or a combination thereof. Apertures on the top surface 194 of the canister housing 192 are generally in the form of a connection port 203, or multiple connection ports, for coupling ancillary devices to the canister itself. More specifically, the connection ports 203 couple the operational circuitry housed within the canister to these ancillary devices, as well as to a lead electrode 191. Connection ports 203 may be positioned anywhere along the canister housing 192, however, in particular embodiments, the connection ports 203 are located at the distal end 200 or proximal end 202 of the canister housing 192. The connection ports 203 may additionally be positioned along the canister housing's sides 198 and bottom surface 196.

In yet another embodiment, connection ports 203 are located at both the distal end 200 and the proximal end 202 of the canister housing 192. Positioning connection ports 203 at both the canister's distal end 200 and the proximal end 202 may enhance the care provided by the S-ICD canister 190. In

particular, this canister arrangement allows the operational circuitry in the S-ICD canister 190 to utilize multiple electrodes and sensors to best regulate and treat the particular condition experienced by the patient recipient. Examples of ancillary devices suitable for attachment include a lead 193, such as a lead for sensing, shocking and pacing. Additional ancillary devices suitable for attachment to the S-ICD canister 190, being known in the art, (e.g., heart failure monitoring sensors) are additionally incorporated as being within the spirit and scope of the present invention.

The top surface 194 of the canister housing 192 may additionally include particular appendages. Appendages are especially useful in anchoring the canister housing 192 in a fixed relative position, or alternatively, in advancing the canister housing 192 within the patient recipient. An example of an appendage that may be incorporated into the top surface 194 of the canister housing 192 is an extending fin. A fin-like appendage may extend from the canister housing 192 in order to better direct the S-ICD canister 190 during the implantation procedure. In this capacity, the extended fin acts as a rudder preventing the advancing S-ICD canister 190 from deviating from its desired path. The extended fin may additionally aid in

preventing the S-ICD canister 190 from displacing from its original position after implantation - particularly in the direction perpendicular to the fin's length. Extending fins suitable for the present invention may extend the entire length of the canister housing 192, or alternatively, a segment of the length. Additionally, extending fins may be disposed on the bottom surface 196 of the canister housing 192 in order to provide similar functions.

Appendages may also aid physicians in advancing the S-ICD canister 190 to a desired location within the patient. Motility-enhancing appendages enable the physician to push, pull or otherwise direct the S-ICD canister 190 in a particular fashion throughout the patient's body. During the procedure, a physician generally attaches a medical instrument to the motility-enhancing appendage. This attachment step may occur either before or after the S-ICD canister 190 has been inserted within the patient. An example of one medical instrument capable of attaching to the motility-enhancing appendage is a hemostat. Other similar medical instruments, known to those skilled in the art, may also be utilized in this attachment step. The physician then advances the hemostat in a desired

direction to properly seat the S-ICD canister 190 within the patient's body.

The surrounding sides 198 of the canister housing 192 are generally smooth and substantially rounded between the top surface 194 and the bottom surface 196 of the canister housing 192. Smoothing the side surfaces 198 aids in the insertion of the S-ICD canister 190 during the implantation procedure. More specifically, smoother side surfaces 198 permit the S-ICD canister 190, as a whole, to slide easily through the surrounding bodily tissue while minimizing abrasion. In addition, rounded, smooth transition surfaces allow the surrounding tissues to better conform to the presence of the device making the device more comfortable to the patient during chronic implantation.

In contrast, sharp edge formations may have the tendency to ablate, or at a minimum, irritate the surrounding tissue during the implantation process. Subsequent tissue irritation may also occur long after the implantation process. Minor fluctuations in the positioning of a sharp edged canister may cause an inflammatory response in the surrounding tissue. These minor fluctuations are often the result of simple day-to-day movements. Movement of the arms, bending at the waist and

rotation of the torso are all daily activities that may cause surrounding bodily tissue to chafe against the installed canister. Smoothing these edges, however, would greatly reduce tissue abrasion, and thereby, reduce the soreness and discomfort associated with the implanted S-ICD canister 190.

Referring now to Figure 20, the bottom surface 196 of the S-ICD canister 190 of Figure 19 is shown. In particular, an electrode 204 possessing an electrically conductive surface is depicted within the confines of, and hermetically sealed within, the S-ICD canister housing 192. Although an electrode 204 is specifically illustrated, any sensor capable of receiving physiological information and/or emitting an energy may be similarly situated on the canister housing 192. For example, a sensor may be located on the canister housing 192 that may monitor a patient's blood glucose level, respiration, blood oxygen content, blood pressure and/or cardiac output.

Specifically with reference to Figure 20, the exposed electrode 204 is electrically coupled to the operational circuitry encased within the canister housing 192. The electrode 204, therefore, performs many of the functions defined by the operational circuitry's programming. More specifically, the electrode 204 is the vehicle that actually receives the

signals being monitored, and/or emits the energy required to pace, shock or otherwise stimulate the heart. Although only a single electrode 204 is shown for illustrative purposes, certain S-ICD canister embodiments 190 may be manufactured with multiple electrodes. For these embodiments, the multiple electrodes are often task specific, wherein each electrode 204 performs a single function. In alternate embodiments, a single electrode 204 may perform both monitoring and shocking functions.

The electrodes 204 are generally positioned at the ends 200 and 202 of the canister housing 192. In the S-ICD canister 190 depicted in Figure 20, the electrode 204 is placed at the distal end 200 of the canister housing 192. Although the electrode 204 is positioned in close proximity to the distal end 200, the side 198 of the canister housing 192 nearest the distal end 200 should generally refrain from exposing any portion of the electrically conductive surface of the electrode 204. Additionally, although the electrode is generally planar, in particular embodiments, the electrode may possess a curved shape.

The size of the electrically conductive surface of an electrode 204, in one particular embodiment, is approximately 500 square millimeters in area. In alternate embodiments, it is

desirable to maintain the size of the electrically conductive surface between approximately 100 square millimeters and approximately 2000 square millimeters in area. As with the size of the canister housing 192, the size of the electrically conductive surface may vary to accommodate the particular patient recipient. Furthermore, the shape and size of an electrode 204 may vary to accommodate the placement of the electrode 204 on the canister housing 192. The shape and size of an electrode may also be varied to adapt to specified diagnostic and therapeutic functions performed by the canister 190. For example, the electrode's 204 size and shape may be altered to minimize energy loss to surrounding bodily tissues, or for minimizing the diversion of current away from the heart.

One factor in minimizing current diversion is in maintaining an equal current density distribution throughout an electrode's 204 conductive surface. A controlling factor in an electrode's 204 current density distribution is the electrode's 204 overall shape. Certain electrode 204 shapes draw current to particular areas on the electrode's 204 conductive surface (e.g., sharp angles). As a result, these electrodes 204 create an unequal current density distribution. Electrodes 204 possessing sharp corners, for example, may have higher current

densities in the regions defined by the sharp corner. This unequal current density distribution results in confined "hot spots". The formation of hot spots may be desirable and intentional, such as when attempting to increase current density adjacent to the sternum. On the other hand, hot spots may be undesirable as these high current density locations may scorch or singe surrounding tissue during the electrode's 204 emission of electrical energy. Moreover, electrodes 204 possessing numerous hot spots on the electrode's 204 conductive surface consequently generate areas of low current density - or "cold spots". This unequal distribution may render the electrode 204, as a whole, highly ineffective.

Electrode 204 embodiments of the present invention, in contrast, are substantially rounded. In particular, regions of the electrode 204 traditionally possessing sharp corners are rounded to prevent extreme hot spots. Nevertheless, the distal most segment of the electrode 200 is slightly angulated in order to modestly concentrate current at the tip, and therefore, direct current more through the mediastinum and into the patient's heart.

Another controlling factor in an electrode's 204 current density distribution is the electrode's 204 overall size. The

relatively small conductive surfaces of electrodes 204 of the present invention, as discussed above, minimize the likelihood of forming either hot or cold spots. Larger electrodes, in contrast, possess large surface areas that may be more prone to generate more regions of unequal current distribution.

As discussed above, electrodes 204 may vary in shape and size to accommodate an assortment of canister housing 192 designs. For illustrative purposes, Figure 20 and Figures 23A-25A show various electrode shapes disposed upon various canister housings 192. The canister housings 192 depicted in these figures, however, are not limited to the electrode shape specifically illustrated.

The electrode 204 depicted in Figure 20 is "thumbnail" shaped. The distal end margin 206 of this shaped electrode 204 generally follows the outline of the rounded distal end 200 of the canister housing 192. As the electrode 204 moves proximally along the length of the canister housing 192, the conductive surface terminates. In the thumbnail embodiment, the electrode's conductive surface is generally contained within the rounded portions of the distal end 200 of the canister housing 192. In alternate embodiments, the electrode's conductive surface may extend proximally further within the canister

housing 192. In yet another thumbnail shaped electrode embodiment, the margins of the electrode's conductive surface refrain from following the exact rounded contour of the canister housing 192.

5 A "spade" shaped electrode 236 is depicted in Figure 23A. The distal end of the spade shaped electrode also generally follows the outline of the rounded distal end 234 of the canister housing 220. As the spade shaped electrode 236 moves proximally along the length of the canister housing 220, the conductive surface terminates in a rounded proximal end. Similar to the thumbnail embodiment described above, the spade shaped electrode's conductive surface is generally contained within the distal end 234 of the canister housing 220. In alternate embodiments, the spade shape electrode's conductive surface may extend proximally further within the canister housing 220. In yet another spade shaped electrode 234 embodiment, the margins of the spade shaped electrode's conductive surface refrain from following the exact rounded contour of the canister housing 220, but substantially form a
10
15
20 spade shaped configuration.

A circular shaped electrode 238 is illustrated in Figure 23B.

A rectangular shaped electrode 246 is shown in Figure 24A. Rectangular shaped electrodes 246 also incorporate electrodes that are substantially rectangular in shape. In particular to Figure 24A, the corners of the rectangular shaped electrode 246 are rounded. Moreover, one margin of the rectangular shaped electrode's conductive surface generally follows the rounding of the distal end 246 of the canister housing 241.

A triangular shaped electrode 254 is depicted in Figure 24B. Triangular shaped electrodes 254 also incorporate electrodes that are substantially triangular in shape. In particular to Figure 24B, the corners of the triangular shaped electrode 254 are rounded.

A square shaped electrode 257 is depicted in Figure 24C. Square shaped electrodes 257 also incorporate electrodes that are substantially square in shape. In particular to Figure 24C, the corners of the square shaped electrode 257 are rounded.

An ellipsoidal shaped electrode 268 is depicted in Figure 25A. The distal end of the ellipsoidal shaped electrode 268 generally follows the outline of the rounded distal end 264 of the canister housing 260. As the ellipsoidal shaped electrode 268 moves proximally along the length of the canister housing 260, the conductive surface elongates and then again reduces in

length to form a rounded proximal end. Similar to the thumbnail and spade shaped embodiments described above, the ellipsoidal shaped electrode's conductive surface is generally contained within the distal end 264 of the canister housing 260. In alternate embodiments, the ellipsoidal shape electrode's conductive surface may extend proximally further within the canister housing 260. In yet another ellipsoidal shaped electrode 264 embodiment, the margins of the ellipsoidal shaped electrode's conductive surface refrain from following the exact rounded contour of the canister housing 260, but substantially form an ellipsoidal shaped configuration.

Energy emissions from any of the above described electrodes 204 generally follow a path of least resistance. The intended pathway of the emission, therefore, may not necessarily be the pathway that the emission ultimately travels. This is particularly a problem with emissions made within the human anatomy where tissue conductivities are highly variable. Obstructing, or low conductivity tissues like bone material, fat, and aerated lung may all redirect released energy away from the heart. Alternatively, surrounding non-cardiac or striated muscle tissue, being generally a high conductivity tissue, may divert energy emissions away from the heart. This is a

particular concern for the pectoralis, intercostal, and latissimus dorsus musculature, as well as other thoracic, non-cardiac musculature found between the treating electrodes of the S-ICD. Since the S-ICD canister 190 of the present invention
5 does not directly contact the heart muscle itself, such low and high conductivity tissues will impede and/or shunt a percentage of the emissions from the present invention's electrode 204 - permitting the heart to receive a fraction of the total emitted energy.

The present invention minimizes the effect of impeding and/or obstructing tissues by designing an electrode 204 and canister housing 192 capable of focusing the electrode's array of emitted energy. Focusing the electrode's array of energy into a highly concentrated beam enables the resulting beam to be only minimally impeded or shunted away by any surrounding bodily tissue. This focused array, therefore, delivers more of the originally emitted energy directly into the mediastinum, and subsequently, into the intended heart muscle than would otherwise occur if the entire canister, or a majority of the
20 canister, were electrically active - as is the case with standard transvenous ICD systems. The present invention provides an electrode 204 and canister housing 192 design that

creates a consistently focused array of energy directed toward the chambers of a recipient's heart.

Generally, it is desirable to have the electrode's longest conductive surface plane positioned perpendicular to the extending ribs within a recipient's rib cage. Aligning the electrode 204 in this manner removes the longest conductive plane from possibly extending directly over any one particular rib. If the longest conductive surface were to extend along the length of a rib, a greater percentage of emitted energy would be distributed through the rib material, and consequently, may fail to reach the heart muscle. When aligned perpendicular to the ribs, only a portion of the conductive surface is directly over any particular rib. This alignment permits only a small percentage of the emitted energy to be obstructed by the impeding rib material. Therefore, in particular S-ICD canister 190 embodiments that extend parallel with a recipient's rib cage, the width 205 of the electrode's conductive surface is approximately greater than or equal to the length 207 of the electrode's conductive surface. This electrode 204 sizing is best illustrated with reference to Figure 20. The conductive surface of the thumbnail-shaped electrode in Figure 20 is depicted as both shallow and wide. In contrast, S-ICD canister

190 embodiments that extend perpendicular with a recipient's rib cage, can have their conductive surface's length 207 being greater than their conductive surface's width 205. The appropriate S-ICD canister 190 alignment, and subsequently the appropriate electrode 204 alignment, is determined by the style of S-ICD canister 190 chosen for the patient recipient. Figures 23A-26C illustrate numerous S-ICD canister housing embodiments 192 for properly positioning an electrode 204 over a recipient's heart. The embodiments depicted, however, are for illustrative purposes only, and are not intended to limit the scope of the present invention.

Another solution to the problem of thoracic tissues interfering with energy delivery is by designing a canister housing 192 that may be strategically positioned in close proximity to the patient's heart. One embodiment of the present invention possesses a curved canister housing 192 that enables the S-ICD canister 190 to be advanced just over the patient recipient's ribcage. Moreover, in another embodiment, the curvature of the S-ICD canister 190 directly mimics the natural curvature of the ribcage.

Referring now to Figure 21, the S-ICD canister 190 of Figure 19 is shown from the side. Figure 21 shows the S-ICD

canister's top surface 194, the bottom surface 196 and the side 198 of the canister housing 192. In the embodiment depicted, both the top surface 194 and the bottom surface 196 of the canister housing 192 are curved. In fact, throughout most of the proximal end 202 of the canister housing 192, the curvature is generally similar, and indeed can be identical, between the top surface 194 and the bottom surface 196. In alternative embodiments of the present invention, the top surface 194 may be generally planar while the bottom surface 196 is curved. In yet another embodiment of the present invention, the top surface 194 may be curved and the bottom surface 196 is generally planar.

Referring back to the embodiment depicted in Figure 21, the curvatures between the top surface 194 and the bottom surface 196 are shown differing toward the distal end 200 of the canister housing 192. At the S-ICD canister's distal end 200, the canister housing's top surface 194 curvature tapers downwardly toward the canister's bottom surface 196. This tapering causes the distal end 200 of the canister housing 192 to be narrower (of a decreased depth) than the canister's proximal end 202. In certain embodiments, this tapering in depth may be gradual throughout the length of the canister's

housing 192, or alternatively, the tapering may be confined to a particular area.

10
15
20
25
30
35
40
45
50
55
60
65
70
75
80
85
90
95
100
105
110
115
120
125
130
135
140
145
150
155
160
165
170
175
180
185
190
195
200
205
210
215
220
225
230
235
240
245
250
255
260
265
270
275
280
285
290
295
300
305
310
315
320
325
330
335
340
345
350
355
360
365
370
375
380
385
390
395
400
405
410
415
420
425
430
435
440
445
450
455
460
465
470
475
480
485
490
495
500
505
510
515
520
525
530
535
540
545
550
555
560
565
570
575
580
585
590
595
600
605
610
615
620
625
630
635
640
645
650
655
660
665
670
675
680
685
690
695
700
705
710
715
720
725
730
735
740
745
750
755
760
765
770
775
780
785
790
795
800
805
810
815
820
825
830
835
840
845
850
855
860
865
870
875
880
885
890
895
900
905
910
915
920
925
930
935
940
945
950
955
960
965
970
975
980
985
990
995
1000

Tapering the depth of the canister housing 192 may improve the overall performance of the S-ICD canister 190. In particular, a tapered distal end 200 may aid in insertion and advancement of the S-ICD canister 190 within the patient recipient's body. A tapered distal end 200 enables the S-ICD canister 190 to easily traverse through narrow subcutaneous spaces. In particular, a physician generally tries to create a passageway into the patient's body that is appropriately sized for the canister, especially in regard to positioning the distal segment of the canister with the end containing the electrode in close proximity to the sternum. Tapering the distal end of the canister eliminates unnecessary trauma to the patient in the tight spaces adjacent to the sternum. For larger canisters, however, this tight subcutaneous space is difficult to traverse. Subsequently, these larger canisters cause the physician to undertake extensive sharp and blunt dissection of the patient's tissues in order to place the larger canister in the desired location. Regardless of the extent of the dissection, however, larger non-tapered distal segments may prove extremely uncomfortable if forced into a parasternal position to satisfy

the needs of focusing energy through the mediastinum, and subsequently, to the patient's heart.

In contrast, embodiments of the present invention having narrow canister housings 192 may easily traverse such passageways. Moreover, tapering the S-ICD canister's distal end 200 further streamlines the canister housing 192, and therefore, enhances the ease of the implantation procedure. Tapering the S-ICD canister's distal end 200 is particularly important when positioning the distal end of the canister housing as near the left border of a patient's sternum as possible. This canister housing 192 placement optimizes energy delivery to the mediastinum, and therefore, to the patient's heart.

The depth of the canister housing 192 is shown as being very narrow as to the canister housing's length 207. The canister's housing depth is less than approximately 15 millimeters. In alternate embodiments, the depth of the canister's housing depth is approximately 5 millimeters to approximately 10 millimeters. At the tapered distal end 200, the canister housing may have a depth of approximately 1-4 millimeters.

In certain embodiments of the present invention, it is desirable to position the S-ICD canister 190 in close proximity

to the patient recipient's heart, without directly contacting the heart. A favored location for this S-ICD canister 190 placement is just over the patient's ribcage. More particularly, in certain embodiments it is favored to place the S-ICD canister 190 just to the left of, and adjacent to, the sternum with a segment at the distal end 200 containing the electrode 204 closest to the sternum. Figure 22 depicts the placement of the S-ICD canister 190 according to one embodiment of the present invention with the lead electrode traversing the subcutaneous tissues laterally toward the axilla and then posteriorly to "catch" the current as it is emitted from electrode 204 parasternally and anteriorly toward the lead electrode 191 as it receives current exiting the posterior mediastinum and paraspinal tissues.

During the implantation procedure, a single incision 210 is made in the left anterior axillary line approximately at the level of the cardiac apex, or around the fifth to the sixth intercostal space. The location of this single incision 210 enables the physician to position both the S-ICD canister 190 and the canister's ancillary devices (e.g., pacing leads, shocking leads, etc.) from this single incision 210. Once this incision 210 is made, the physician may insert surgical

instruments or a specially designed tool (not shown) through the incision 210 to shape a passageway for the S-ICD canister 190 to navigate. Although a tool may be utilized in particular embodiments, a tool is not required - standard surgical
5 instruments, together with the general shape of the S-ICD canister 190, are sufficient to facilitate proper positioning of the device in the left anterior thorax as adjacent as possible to the sternum.

In particular embodiments, a physician advances both the S-ICD canister 190 and the lead electrode 191 within the patient to form a depolarization vector with respect to the patient's heart 218. The depolarization vector is a vector having an origin, a first end point and a second end point.

In one embodiment, the origin of the depolarization vector originates approximately within the chambers of the patient's heart 218. Similarly, the first vector end point comprises the S-ICD canister electrode's 204 positioning with respect to the patient's heart 218. Finally, the second vector end point comprises the lead electrode's 191 positioning with respect to
20 the patient's heart 218. In alternate embodiments, the second vector end point comprises a second canister electrode.

The lead electrode may be positioned at various positions within the body because the length of the lead 193 may be varied. For example, S-ICD devices of the present invention may have leads with lengths between 5 centimeters and 55 centimeters. Therefore, the S-ICD canister 190 and lead electrode 191 of the present invention may create numerous depolarization vectors.

In particular embodiments, a degree of separation of 180 degrees or less exists between the S-ICD canister electrode 204 and the lead electrode 191. In alternative embodiments, the degree of separation between the S-ICD canister electrode 204 and the lead electrode 191 is approximately 30 degrees to approximately 180 degrees.

In order to obtain the desired degree of separation for the depolarization vector, generally one device (either the S-ICD canister 190 or the lead electrode 191) must be advanced anteriorly while the other device is advanced posteriorly from the initial incision 210. Accordingly, when the S-ICD canister 190 is advanced subcutaneously and anteriorly from the incision 210, the lead electrode 191 must be advanced subcutaneously and posteriorly from the incision 210. With this particular embodiment, a physician may advance the S-ICD canister 190

medially toward the patient's left inframammary crease to a location proximate the patient's sternum 212.

Alternatively, the physician may advance, and subsequently position the S-ICD canister 190 within the anterior portion of the patient's ribcage 216. This anterior placement may further include the patient's left parasternal region, an anterior placement within the region of the patient's third and the patient's twelfth rib 214, or generally any subcutaneous ribcage 216 placement anterior to the patient's heart 218. In order to complement the S-ICD canister's 190 placement, and obtain the correct depolarization vector, the lead electrode 191 must be advanced posteriorly toward the paraspinal or parascapular region of the patient's ribcage 216.

In another embodiment of the present invention, the spatial positioning of the S-ICD canister 190 and the lead electrode 191, described in detail above, are reversed.

Referring back to Figure 21, the curvature of particular S-ICD canister embodiments 190 may be designed to generally mimic the natural curvature of a patient's ribcage 216. These S-ICD canister embodiments 190 restrict canister displacement and heighten comfort for the patient implanted with the S-ICD canister 190. The anatomical shape of a patient recipient's

ribcage 216 varies. The present invention includes numerous S-
ICD canister housing 192 curvatures to accommodate these varying
shapes. In particular, the present invention includes S-ICD
canisters 190 sized and shaped to properly fit children, as well
5 as ones to properly fit fully developed adults.

The curvature of the canister housing 192 is generally arc-
shaped. The degree of curvature for any particular embodiment
of the present invention is measured through a curvature vector
theta (θ). The curvature vector θ is a vector having an origin
199, a first end point and a second end point.

In one embodiment, the origin 199 of the curvature vector θ
originates approximately at the center of the S-ICD canister 190
(lengthwise). The first vector end point in this embodiment
comprises the distal end 200 of the S-ICD canister 190 and the
second vector end point comprises the proximal end 202 of the S-
ICD canister 190. In particular embodiments, the curvature
vector θ possesses a degree of separation between 30 degrees and
180 degrees. For example, a canister housing 192 having a
degree of separation of 180 degrees is planar. Decreasing the
20 degree of curvature θ causes the canister housing to become more
arcuate in shape.

0000059-0327014 02280-55504660

In alternative embodiments, the origin 199 of the curvature vector θ may originate at a point other than the center of the S-ICD canister 190. Origins 199 shifted from the center of the S-ICD canister 190 produce regions of greater curvature, as well as areas of lesser curvature, in the same S-ICD canister 190. Similarly, a S-ICD canister 190 may possess multiple curvature vectors θ having origins 199 throughout the length of the S-ICD canister 190. Multiple curvature vectors θ produce various non-linear or nonsymmetrical curves that, in certain circumstances, remain generally arc-shaped. Canister housings possessing multiple curvature vectors θ are particularly suitable for S-ICD canister 190 placement near the patient's sides (generally in the area under the patient's arms where the thorax has a more marked degree of curvature). Canister housings 192 incorporating a nonsymmetrical curvature are generally longer S-ICD canisters 190 that span over the front and sides of the patient's ribcage. In particular, these S-ICD canisters 190 span areas of the ribcage 216 that are generally planar (around the patient's sternum 212), as well as areas that are highly curved (generally in the area under the patient's arms).

Curved canister housings 192 are generally for S-ICD canisters 190 that extend lengthwise, or approximately

horizontally, along the length of the ribs in the ribcage 216. For certain embodiments, however, it is desired to orient the length of the S-ICD canister 190 to be perpendicular to the length of the ribs in the ribcage 216. A perpendicularly orientated S-ICD canister 190 generally requires very little, if any, curvature to conform to the ribcage 216.

Figures 23A-26C depict particular S-ICD canister 190 designs. In each of these particular S-ICD canister designs, the various material constructions, dimensions and curvatures, discussed in detail above, may be incorporated within each individual S-ICD canister design. Furthermore, particular aspects of any individual S-ICD canister design may be incorporated, in whole or in part, into another depicted S-ICD canister design.

Turning now to Figure 23A, a S-ICD canister 220 having a duckbill-shaped canister housing 222 is shown. The duckbill-shaped canister housing 222 has a proximal end 226 and a distal end 234. The proximal end 226 of the duckbill-shaped canister housing 222 further includes a main housing member 228 and a distal housing member 230. The distal housing member 230 is an elongated segment extending distally from the distal end of the main housing member 228. Although the two segments differ in

their size and shape, the distal housing member 230 and main housing member 228 are generally contiguously and fluidly attached to one another and may be formed from a single mold. In alternative embodiments, however, the distal housing member 5 230 may be hinged to the main housing member 228. The distal housing member 230 also generally comprises a material that is similar in composition to that forming the main housing member 228. In alternate embodiments, however, the distal housing member 230 may include a material that possess enhanced electrically insulated characteristics.

The main housing member 228 generally encases the operational circuitry, batteries and capacitors of the duckbill-shaped S-ICD canister 220. The width and length of the main housing member 228 enable the main housing member 228 to accommodate batteries and capacitors for delivering a shocking energy of approximately 50 J of energy, 75 J of energy, 100 J of energy, 125 J of energy, 150 J of energy and 200 J of energy.

Although a specific number of batteries and capacitors are required for delivering these charges, their positioning within 20 the canister housing 222 is highly modifiable. More specifically, the width of the main housing member 228 may be altered to accommodate a longer or shorter canister. For

example, the width of the main housing member 228 may be increased in order to obtain a main canister housing 228 of decreased length. Modification of the sizing and orientation of the main housing member 228 allow manufacturers to create a variety of differing sized duckbill-shaped S-ICD canisters 220. Increased specificity in the canister housing's shape and size enhance the comfort and wearability for the patient recipient.

In general, the width of the main housing member 228 is approximately 10 cm wide or less. Likewise, the length of the main housing member 228 is approximately 20 cm long or less. In particular embodiments the width of the main housing member 228 is 4 cm. In an alternative embodiment, the width of the main housing member 228 is 8 cm.

The distal housing member 230 is an elongated segment of canister housing that possesses a width that differs from that of the main housing member 228. The distal housing member's width decreases as the distal housing member 230 extends distally. This tapering in width results in the formation of a shoulder region 232. In particular embodiments, the rate with which the width decreases as the proximal housing member 230 extends distally is constant. In alternate embodiments, the rate is variable. A variable rate shoulder region 232 taper

proceeds at a rate of tapering where a unit of tapering width is not directly related to a unit of length in the distal direction. In either of the embodiments, however, bilateral symmetry is maintained throughout the length of the distal housing member 230.

The shoulder region 232 is a generally rounded and smooth region of the canister housing 222. As discussed in detail above, rounding the edges along the canister's surface enhances insertion of the S-ICD canister 220. The rounded edges also reduce abrasion and inflammation associated with short-term and long-term wearability.

Extending distally beyond the shoulder region 232 is the distal head 234 of the distal housing member 230. The distal head 234 is the distal termination point of the duckbill-shaped S-ICD canister 220. The distal head 234 includes a generally rounded end. In one embodiment, illustrated in Figure 23B, the distal head 234 has a width greater than the width at a location within the shoulder region 232 of the distal housing member 230. In alternative embodiments, the distal head's width is equal to or less than the width at any point in the shoulder region 232 of the distal housing member 230, as illustrated in 23A.

The length of the duckbill-shaped S-ICD canister 220 may depend highly upon the shape and size of the distal housing member 230. In particular embodiments, the duckbill-shaped S-ICD canister 220 is approximately 30 centimeters long or less.

5 In alternative embodiments, the duckbill-shaped S-ICD canister 220 is approximately 10 centimeter or less. In particular embodiments, the length of the duckbill-shaped S-ICD canister 220 may be curved, or alternatively, or a portion of the length (i.e., the shoulder region 232 and distal head 234) are curved.

10 The electrode 236 for the duckbill-shaped S-ICD canister 220 is generally seated within a portion of the distal housing member 230. Figure 23A diagrams in phantom the approximate location of an electrode 236 on the duckbill-shaped canister housing 222. Although the electrode 236 is depicted as generally circular in shape (in Figure 23B), the electrode may also be "spade shaped" (depicted in Figure 23A), thumbnail shaped, square, rectangular, triangular or ellipsoidal. The electrode 236 is electrically coupled to the operational circuitry within the main housing member 228 of the S-ICD
15
20 canister 220.

In certain embodiments of the present invention, an associated feature of the electrode 236 at the distal end is the

presence of a margin of insulated material 237 around the active electrode 236. The margin of insulated material 237 may aid in directing emitted energy from the electrode 236 inwardly toward the patient's heart instead of dispersing energy outward toward the patient's chest wall. This margin of insulated material 237 typically ranges from 1-5 mm in width and may extend to the margin of the housing. Moreover, in certain embodiments, the margin of insulated material 237 comprises a ceramic material or other material designed to facilitate focusing of current inward toward the heart.

In certain embodiments of the present invention, the electronic components (e.g., circuitry, batteries and capacitors) of the S-ICD canister 220, are generally absent from the distal housing member 230. As such, the depth of the distal housing member 230 may be greatly reduced. In these embodiments, a depth of approximately 1 millimeter may be obtained at the distal head 234 of the duckbill-shaped S-ICD canister 220.

The duckbill-shaped distal housing member 230 enhances navigation during canister implantation. The distal head 234 of the distal housing member 230 is blunt at its end to reduce trauma suffered to surrounding tissue during the S-ICD

canister's advancement or during chronic implantation. Similarly, the narrower distal head 234 (width-wise and depth-wise) is easier to control during the advancement procedure. The smaller distal head 234 also enables a physician to navigate
5 the smaller and more compact tissues adjacent to the sternum, which a larger head might otherwise find unobtainable. Moreover, the narrower distal head 234 may be advanced to a location in close proximity to the patient recipient's heart 218 without concern of distorting or stressing the skin in the left
10 parasternal region.

The closer the electrode 236 is to the patient's heart 218, the less energy is required to achieve an adequate electric field or current density to defibrillate the heart. A desirable anatomical position for reducing this energy requirement is just
15 lateral to the sternum 212 of the patient. The area surrounding the patient's sternum 212 generally lacks a considerable accumulation of bodily tissue. Thus, subcutaneous S-ICD canister 190 positioning over the sternum 212, or some other
20 location just over the rib cage 216, provides a significant lessening of the required energy - due to proximity to the heart 218 and a reduction in impeding surrounding tissue. Positioning an ICD canister of normal contour in this area has proven

difficult, however, and is additionally aesthetically displeasing. The reduced profile of the duckbill-shaped S-ICD canister 220, however, provides such optimal electrode 236 placement in a more aesthetically and less physically obtrusive manner.

Structurally, a reduction in the energy requirement frees space within the canister housing 222. This space was previously occupied by batteries and capacitors needed for the higher energy requirements. This space, however, is no longer required. The duckbill-shaped S-ICD canister 220, therefore, can be smaller in length, width and depth. Eliminating batteries and capacitors also reduces the weight of the present invention. As described in detail above, reducing the weight of the S-ICD canister enhances patient recipient comfort.

Figure 24A illustrates another embodiment of a S-ICD canister having a generally rectangular-shaped canister housing 240. The rectangular-shaped canister housing 240 includes a top surface 241, a bottom surface (not shown) and surrounding sides 248 connecting these two surfaces. The rectangular-shaped canister housing 240 further includes a distal end 242 and a proximal end 244. The electrode 246, shown in phantom, is generally positioned at either the distal end 242 or the

proximal end 244 of the canister housing 240. In alternative
embodiments, the rectangular-shaped canister housing 240 may
include two or more electrodes 246. When two electrodes are
utilized, one electrode is positioned at the distal end 242 of
5 the canister housing 240 while the second electrode is
positioned at the proximal end 244 of the canister housing 240.

The length of the rectangular-shaped canister housing 240
is approximately 30 centimeters long. In alternative
embodiments, the rectangular-shaped canister housing 240 is
10 approximately 10 centimeter long or less. The width of the
rectangular-shaped canister housing 240 is approximately 3
centimeters to approximately 10 centimeter wide.

Figures 24B and 24C depict additional embodiments of a S-
ICD canister having a generally square-shaped canister housing
250. The square-shaped canister housing 250 includes a top
surface 251, a bottom surface (not shown) and surrounding sides
252 connecting these two surfaces. The sides 252 of the square-
shaped canister housing are generally of the same length. The
electrode 254, shown in phantom, is generally positioned in the
20 center and to one side of the square-shaped canister housing
250. A triangular shaped electrode 254 is specifically
illustrated at the corner of the square-shaped canister housing

250 in Figure 24B. In alternate embodiments, however, the electrode 254 may be positioned toward the center of one of the sides 252 of the square-shaped canister housing 250, or at the center of the square-shaped canister housing 250, or rotated
5 more. A square shaped electrode 257 is specifically illustrated at the side of the canister housing 250 in Figure 24C.

The length and width of the square-shaped canister housing 250 is approximately 6 centimeters to approximately 8 centimeter long and wide.

10 Figure 25A depicts yet another embodiment of a S-ICD canister having a "tongue depressor-shaped" canister housing 260. The tongue depressor-shaped canister housing 260 includes a top surface 261, a bottom surface (not shown) and surrounding sides 262 connecting these two surfaces. The tongue depressor-shaped canister housing 260 further includes a distal end 264
15 and a proximal end 266. The distal end 264 and the proximal end 266 of the tongue depressor-shaped canister housing 260, however, are rounded. In one embodiment, the rounded ends extend outwardly away from the canister housing 260 in either
20 the corresponding distal or proximal direction. The rounded ends generally are circular arc-shaped curves, however, the

rounded ends may also be elliptical or nonsymmetrical arc-shaped curves.

The electrode 268, shown in phantom, is generally positioned at either the distal end 264 or the proximal end 266 of the canister housing 260. In alternative embodiments, the tongue depressor-shaped canister housing 260 may include two or more electrodes 268. When two electrodes are utilized, one electrode is positioned at the distal end 264 of the canister housing 260 while the second electrode is positioned at the proximal end 266 of the canister housing 260.

The length of the tongue depressor-shaped canister housing 260 is approximately 30 centimeters long or less. In alternative embodiments, the tongue depressor-shaped canister housing 260 is approximately 15 centimeter long or less. The width of the tongue depressor-shaped canister housing 260 is approximately 3 centimeters to approximately 10 centimeters wide.

Referring now to Figure 25B, where a modified tongue depressor-shaped canister housing 270 is shown. The modified tongue depressor-shaped canister housing 270 is similar to the tongue depressor-shaped S-ICD canister 260 depicted in Figure 25A, however, the modified tongue depressor-shaped canister

housing 270 comprises only has a single rounded distal end 272. The proximal end 274 of the modified tongue depressor-shaped canister housing 270 is generally square.

Figures 26A-26C illustrate another embodiment of a S-ICD canister having a multi-segment canister housing 280. The multi-segment canister housing 280 includes at least two canister housing segments that are coupled together. The S-ICD canister depicted in Figure 26A, 26B and 26C specifically have a distal segment 282 and a proximal segment 284 hinged, or otherwise coupled, together.

The distal segment 282 includes a top surface 292, a bottom surface (not shown) and surrounding sides 286 connecting these two surfaces. The distal most end 288 of the distal segment 282 comprises a rounded region. An electrode 290 is disposed within this rounded region of the distal segment 282 (shown in phantom). The electrode 290 generally follows the outline of the rounded region of the distal most end 288 of the canister housing, however, the electrode 290 may comprise of other shapes and sizes.

In an embodiment of the multi-segment canister housing 280, both the electrode 290 and the electronics are disposed within the distal segment 282. In alternative embodiments, the

electrode 290 is disposed within the distal segment 282 and the electronics are located within the proximal segment 284 of the multi-segment canister housing 280.

Figure 26B shows the distal segment 282 of the multi-segment canister housing 280 being curved to mimic the anatomical shape of a patient recipient's ribcage 216. In the embodiment depicted, both the top surface 292 and the bottom surface 294 of the proximal segment 282 are curved. The curvature, however, differs at the distal most end 288 of the distal segment 282. At the distal segment's distal most end 288, the distal segment's top surface 292 tapers downwardly toward the distal segment's bottom surface 294. This tapering causes the distal most end 288 of the distal segment 282 to be narrower than the distal segment's distal end 296. In certain embodiments, this tapering in depth may be gradual throughout the length of the distal segment 282, or alternatively, the tapering may be confined to a particular area.

The proximal segment 284 also includes a top surface 298, a bottom surface 300 and surrounding sides 302 connecting these two surfaces. The proximal segment 284 depicted in Figure 26B, however, is generally planar. In alternative embodiments, depicted in Figure 26C, the proximal segment 284 may also be

curved and may also be of a different curvature to that of the distal segment.

The length of the multi-segment canister housing 280 is approximately 30 centimeters long or less. In alternative
5 embodiments, the multi-segment canister housing 280 is approximately 20 centimeters or less. In yet another embodiment, the multi-segment canister housing 280 is approximately 12 centimeters or less. The width of multi-segment canister housing 280 is approximately 3 centimeters to approximately 10 centimeters wide.

Numerous characteristics and advantages of the invention covered by this document have been set forth in the foregoing description. It will be understood, however, that this disclosure is, in many aspects, only illustrative. Changes may be made in details, particularly in matters of shape, size and arrangement of parts without exceeding the scope of the invention. The invention's scope is defined, of course, in the language in which the appended claims are expressed.